芯伯乐®
XINBOLE

Product Specification

XBLW LM2902

Quad Operational Amplifier


WEB | www.xinboleic.com




Descriptions

The LM2902 consists of four independent, high gain operational amplifiers with frequency compensation implemented internally.It suits for radio recorders and audio systems as tone equalization network and also used in other situations.


The chip is available in DIP 14 (Power Dissipation : 720mW) and SOP 14 plastic package(Power Dissipation : 400mW).



DIP-14



SOP-14



TSSOP-14

Feature

- No External Phase Compensation Circuit Required
- Supply Voltage Range:
  Single Power Supply: Vcc=3~32V
  Dual Power Supply: Vcc = ±1.5V~±16V
- Low Power Consumption: Icc = 0.6mA (typical) (RL = ∞)
- Input Voltage Range Close To Ground Level

Applications


- Transducer Amplifiers
- DC Gain Blocks
- Conventional Op Amp Circuits

Ordering Information

Product Model	Package Type	Marking	Packing	Packing Qty
XBLW LM2902N	DIP-14	LM2902N	Tube	1000pcs/ Box
XBLW LM2902DTR	SOP-14	LM2902	Tape	2500pcs/ Reel
XBLW LM2902TDTR	TSSOP-14	LM2902	Tape	3000pcs/ Reel

XBLW/XINBOLE


CIRCUIT DIAGRAM



PRINCIPLE INTRODUCTION

LM2902 is composed of four identical operational amplifiers. The unit circuit is shown in the figure. Its working principle is briefly described as follows:
The input signal is added to the base of T1 and T4, and after differential amplification;
T8 and T9 form the intermediate stage in compound amplification;the output stageis composed of T10 ~ T13. Among them, T12 is a protection tube. When the output current is too large , thevoltage drop on R increases, causing T12 to saturate conducting, and the collector potential of T12 decreases to nearly 1/2 Vcc, so that the push-pull tubes T10, T11 and T13 are cut off, thereby playing a protective role.
Capacitor C is a phase compensation capacitor.

PIN CONNECTIONS



PINS CONFIGURATION

NO.	Function	Symbol	NO.	Function	Symbol
1	Output 1	OUT 1	8	Output 3	OUT 3
2	Reverse Input 1	IN - (1)	9	Reverse Input 3	IN - (3)
3	Forward Input 2	IN+ (2)	10	Positive Input 3	IN+ (3)
4	Power Supply	VCC	11	Ground	GND
5	Forward Input 2	IN+ (2)	12	Positive Input 4	IN+ (4)
6	Reverse Input 2	IN - (1)	13	Reverse Input 4	IN - (4)
7	Output 2	OUT 2	14	Output 4	OUT4

XBLW XINBOLE

ABSOLUTE MAXIMUM RATINGS

TA=25℃,unless otherwise noted

Parameter Name	Symbol	Test conditions	Rating	Unit
Power Supply	Vcc		32	V
Differential Input Voltage	V_{ID}		32	V
Maximum Input Voltage	V_{IN}		-0.3~32	V
Allowable Power Dissipation	P_D	DIP SOP	720 400	mW
Operating Temperature	Topr		-20~+85	℃
Storage Temperature	Tstg		-55~+125	℃

ELECTRICAL CHARACTERISTICS


Unless otherwise noted, Tamb =25℃

Parameters	Symbol	Test conditions	Min.	TYP.	Max.	Unit
Input Offset Voltage	V_{IO}			3	7	mV
Input Offset Current	I_{IO}	Iin（+）/Iin（-）		5	50	nA
Input Bias Current	I_{BA}			45	250	nA
Input Common Mode Voltage Range	V_{ICM}		0		Vcc-1.5	V
Common Mode Rejection Ratio	K_{CMR}		65	80		dB
Strong Signal Voltage Gain	G_V	Vcc=1.5V，RL≥2KΩ	25	100		V/mA
Output Voltage Range	V_O		0		Vcc-1.5	V
Power Supply Ripple Rejection Ratio	P_{SRR}		65	100		dB
Channel Separation	C_S	f=1kHz~20kHz		120		dB
Current Consumption (1)	I_{CC}			0.6	2	mA
Current Consumption (2)	I_{CC}	Vcc=20V		1.5	3	mA
Output Current (1)	I_O	V_{in}^+=1V，V_{in}^-=0V	20	40		mA
Output Current (2)	I_O	V_{in}^+=0V，V_{in}^-=1V	10	20		mA

XBLW/XINBOLE


TEST PARAMETER DIAGRAM

Null refers to the Amplifier.




CMR=20log| (Ec1-Ec2) (1+R2/R1) / (Vf5-Vf6|

Common-mode rejection CMR and common-mode input voltage range VICM test chart




Gv= (Ek1-Ek2) (1+R2/R1) / (Vf8-Vf7)

Voltage gain Gv test diagram




PSRR (+) =20log| (Vcc1-Vcc2) (1+R2/R1) / (Vf9-Vf10) |




PSRR (-) =20log| (Vee1-Vee2) (1+R2/R1) / (Vf11-Vf12|

Power ripple rejection ratio PSRR test diagram



Vio=Vf1/ (1+R2/R1)


Input offset voltage Vio test diagram




Iio= (Vf2-Vf1) /R (1+R2/R1)

Input offset current Iio test diagram


XBLW XINBOLE



Input bias current IBA test diagram



Consumption current Icc and output current Io test diagram



SW：A

$Cs(A \rightarrow B)=20\log(R2 * V_{OA})/(R1 * V_{OB})$


SW： B

$Cs(B \rightarrow A)=20\log(R2 * V_{OB})/(R1 * V_{OA})$


Channel separation Cs test diagram

XBLW/XINBOLE

APPLICATIONS




The LM2902 is used in five-frequency tone control circuits




Other applications of LM2902

CHARACTERISTIC CURVES



Supply voltage (V)
Input voltage range





Power supply voltage (V)
Power consumption


Package Information

· DIP-14

Size / Symbol	Dimensions In Millimeters		Size / Symbol	Dimensions In Inches	
	Min(mm)	Max(mm)		Min(in)	Max(in)
A	3.710	4.310	A	0.146	0.170
A1	0.510		A1	0.020	
A2	3.200	3.600	A2	0.126	0.142
B	0.380	0.570	B	0.015	0.022
B1	1.524(BSC)		B1	0.060(BSC)	
C	0.204	0.360	C	0.008	0.014
D	18.800	19.200	D	0.740	0.756
E	6.200	6.600	E	0.244	0.260
E1	7.320	7.920	E1	0.288	0.312
e	2.540(BSC)		e	0.100(BSC)	
L	3.000	3.600	L	0.118	0.142
E2	8.400	9.000	E2	0.331	0.354










XBLW/XINBOLE


· SOP-14

Size / Symbol	Dimensions In Millimeters		Size / Symbol	Dimensions In Inches	
	Min(mm)	Max(mm)		Min(in)	Max(in)
A	1.350	1.750	A	0.050	0.068
A1	0.100	0.250	A1	0.004	0.009
A2	1.100	1.650	A2	0.040	0.060
B	0.330	0.510	B	0.010	0.020
C	0.190	0.250	C	0.007	0.009
D	8.550	8.750	D	0.330	0.340
E	3.800	4.000	E	0.150	0.150
e	1.27		e	0.05	
H	5.800	6.200	H	0.220	0.240
h	0.250	0.500	h	0.009	0.020
L	0.400	1.270	L	0.015	0.050
k	8° (max)		k	8° (max)	












XBLW XINBOLE

· TSSOP-14

Size / Symbol	Dimensions In Millimeters		Size / Symbol	Dimensions In Inches	
	Min(mm)	Max(mm)		Min(in)	Max(in)
A		1.200	A		0.047
A1	0.050	0.150	A1	0.002	0.006
A2	0.800	1.050	A2	0.031	0.041
b	0.190	0.300	b	0.007	0.012
c	0.090	0.200	c	0.004	0.0089
D	4.900	5.100	D	0.193	0.201
E	6.200	6.600	E	0.244	0.260
E1	4.300	4.500	E1	0.169	0.176
e	0.65		e	0.0256	
L	0.450	0.750	L	0.018	0.030
L1	1.00		L1	0.039	
k	0°	8°	k	0°	8°







XBLW/XINBOLE

Statement:

- XBLW reserves the right to modify the product manual without prior notice! Before placing an order, customers need to confirm whether the obtained information is the latest version and verify the completeness of the relevant information.
- Any semi-guide product is subject to failure or malfunction under specified conditions. It is the buyer's responsibility to comply with safety standards when using XBLW products for system design and whole machine manufacturing. And take the appropriate safety measures to avoid the potential in the risk of loss of personal injury or loss of property situation!
- XBLW products have not been licensed for life support, military, and aerospace applications, and therefore XBLW is not responsible for any consequences arising from the use of this product in these areas.
- If any or all XBLW products (including technical data, services) described or contained in this document are subject to any applicable local export control laws and regulations, they may not be exported without an export license from the relevant authorities in accordance with such laws.
- The specifications of any and all XBLW products described or contained in this document specify the performance, characteristics, and functionality of said products in their standalone state, but do not guarantee the performance, characteristics, and functionality of said products installed in Customer's products or equipment. In order to verify symptoms and conditions that cannot be evaluated in a standalone device, the Customer should ultimately evaluate and test the device installed in the Customer's product device.
- XBLW documentation is only allowed to be copied without any alteration of the content and with the relevant authorization. XBLW assumes no responsibility or liability for altered documents.
- XBLW is committed to becoming the preferred semiconductor brand for customers, and XBLW will strive to provide customers with better performance and better quality products.

Specification information

Version	Release Date	New/Revised Content
V1.0	2023/10	Initial Writing
V2.0	2025/05	Curve update, template update.

XBLW/XINBOLE