

温度计 使用说明书

1.规格



(1) 温度计身

型号	BK191
解析度	1℃
温度范围	0~600℃
实用感应器	镍铬，镍铬热电偶
准确度	±3℃（在300~500℃）
显示	3 1/2液晶显示屏显示数字
	干电池衰弱警示
电池	006P, 9伏干电池
干电池寿命	超过150小时
外形体积	长160x宽80x高43mm
重量	约200克
工作环境温度	0~40℃

(2) 附件

感应器 (10个)
006P 9伏干电池 (1个)

2.部件名称





- A. 按钮
- B. 环形垫片
- C. 推杆
- D. 终端
- E. 感应器
- F. 测量点

3.使用说明

- (1) 打开温度计背面的电池槽，置入干电池，必须放置妥当。
- (2) 将环形垫片套入推杆。
- (3) 将感应器红边置入红色终端，蓝边置入蓝色终端。按下推钮，将另一端接上导柱。
- (4) 打开电源开关，检视显示屏。当显示屏显示常温时，温度计便可使用。
- (5) 烙铁头沾上焊剂，使用烙铁头触及测试点，在2~3秒内，将显示温度。
- (6) 不使用时，关掉电源。

4.注意事项

- (1) 感应器是用非常铁细（直径0.2mm）丝线制成，应小心使用，切勿弯曲，否则断裂。
- (2) 温度计外壳是用塑料制成，不可触及烙铁头。
- (3) 测量点镀上特殊合金，长时使用，合金层会损耗，测量便不准确，需更换新的感温器后。其寿命约为50次测量。
- (4) 可用酒精清洁附在终端上的任何助焊剂。切勿使用稀溶剂或挥发油。
- (5) 如果显示屏显示 ，表示感温器已报废，要更换感温器。
- (6) 如果显示 ，表示电池已衰弱，不能正常测量温度，需更换电池。

5.更换部件

编号	名称	数量
191-211	感应器	10个

*上列规格可能变更，恕不另行奉告

Bakon[®]
以科技为本 造世界品牌

深圳市白光电子科技有限公司
SHENZHEN BAKON ELECTRONIC TECHNOLOGY CO.,LTD.

全国统一服务热线：400-0988-936

总部地址(ADD)：深圳市光明新区马田街道瑞辉大厦9楼

制造工厂(MFR)：河南白光工具有限公司

生产地址(ADD)：河南省郑州市航空港区锦荣信息科技园7栋

电话(TEL)：0755-89575688 公众号(MP)：BAKON白光

网址(SITE)：www.bakon.cn Email：postmaster@bakon.cn

产品保修卡 (主卡)

Repair Warranty (Principle)

产品型号: _____ Model: _____
使用单位: _____ Customer: _____
出厂编号: _____ Product No: _____
出厂时间: _____ Date of Production: _____
购机日期: _____ Date of Purchase: _____
发卡人: _____ Issued by: _____

由购买日起, 提供_____月保修
From the date of purchasing, we provide _____ months repair warranty

售后服务客户意见书 (副卡)

After Sale Suggestion (Subordinate)

用户: _____
Customer: _____
发出日期: _____ 电话号码: _____
Delivery Date: _____ Tel: _____
用户地址: _____
Address: _____
经销商名称: _____
Distributor: _____
票据号码: _____ 发票日期: _____
Invoice NO: _____ Invoice Date: _____
产品型号: _____ 机身编号: _____
Product Model: _____ Product NO: _____

保修条例:

1. 用户须在购物后一个月内将保修登记卡副卡寄往本公司, 您方可享受我司提供的免费保修。
2. 保修产品时, 保修卡和购机单据, 若两者手续不全则不在免费保修范围。
3. 产品凡因人为损坏, 如: 不按说明书操作使用, 接入不适当电源或非经本公司维修中心认可自行维修等, 均不属于本保修范围。
4. 保修期满后, 为了能更持久完善地为您提供服务, 我们将酌情收取成本费。

Warranty Terms:

1. The table for feedback from customers should be returned to our company within a month after the date of purchase. In this way, customers may enjoy one-month repair warranty.
2. Repair Warranty and Purchase Certificate should be presented. The warranty only applies when all the required documents are available.
3. The warranty does not apply when the equipment has received damage through abuse, carelessness, improper installation, accident or mishandling during shipment, connecting to improper line voltage, or has been serviced by anyone other than an authorized factory representative.
4. After the warranty period, we are ready to provide charged repair service, perfect as always.

尊敬的客户:

非常感谢您选用本公司产品, 为了进一步改善产品质量和加强彼此之间的交流, 敬请留下您宝贵的意见。

Dear Sir / Madam:

Thank you for purchasing our products.To improve our service and ensure the proper use of our products,please kindly write down your suggestions.

名称:
Name of Product: _____

采购日期:
Date of Purchase: _____

建议:
Your Suggestions: _____

包装:
Package: _____

性能:
Functions: _____

其它:
Others: _____

日期:
Date: _____

Bakon[®]

合格证

GUARANTEE CARD

本产品经检验符合技术标准
The product conforms to the technical standards

检验员
Q.C.



深圳市白光电子科技有限公司
SHENZHEN BAKON ELECTRONIC TECHNOLOGY CO.,LTD.

产品保修卡

Warranty card

本产品保修期自购买日起十二个月内有效, 凡属产品质量问题, 凭本卡及收据由本公司负责免费维修。我公司收到返修机后, 2个工作日内修好并返还给客户。

The warranty is valid in one year since the purchase of this ,any quality problem found,please send back to us with courier fee to be collected,upon receipt of the returning unit,we will repair it and send back to customer within two working days.

注: 本产品返厂维修时, 必须附上保修卡, 否则将不予以免费维修, 谢谢合作!

Notice:Please enclose the warranty card along with the returning product, or else we have the right to reject the repairing,thanks for your corporation.