SIEMENS

Data sheet 3RA2155-4JA37-0AK6

	Fuseless motor starter Direct start 600VAC Size S2 54-65Amp 110/120VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC (contactor)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
 of the supplied contactor 	3RT2037-1AK60
 of the supplied circuit-breakers 	3RV2032-4JA15
 of the supplied link module 	3RA2931-1AA00
General technical data	
size of the circuit-breaker	S2
size of load feeder	S2
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
number of poles for main current circuit design of the switching contact	3 electromechanical
design of the switching contact	
	electromechanical
design of the switching contact adjustable current response value current of the current-	electromechanical
design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 54 65 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 54 65 A 690 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 54 65 A 690 V 690 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions trip class	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 54 65 A 690 V 690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37

JL/CSA ratings			
full-load current (FLA) for 3-phase AC motor			
at 480 V rated value	65 A		
at 600 V rated value	54 A		
yielded mechanical performance [hp]			
for single-phase AC motor			
— at 110/120 V rated value	5 hp		
— at 230 V rated value	10 hp		
• for 3-phase AC motor	·		
	20 hp		
— at 220/230 V rated value	20 hp		
— at 460/480 V rated value	50 hp		
— at 575/600 V rated value	50 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (Iq)	magnotic		
at 400 V according to IEC 60947-4-1 rated value	150 000 A		
nstallation/ mounting/ dimensions	100 000 71		
mounting position	vertical		
fastening method		rew-mounted with addition	onal nush-in lug
height	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 274 mm		
width	55 mm		
depth	150 mm		
required spacing	130 11111		
• for grounded parts			
— forwards	0 mm		
— backwards	0 mm		
	50 mm		
— upwards			
— at the side	10 mm		
— downwards	10 mm		
• for live parts			
— forwards	0 mm		
— backwards	0 mm		
— upwards	50 mm		
— downwards	10 mm		
— at the side	10 mm		
onnections/ Terminals			
type of electrical connection for main current circuit	screw-type terminals		
type of connectable conductor cross-sections for main contacts stranded	1 50 mm², 2x (1 25 mm²)		
connectable conductor cross-section for main contacts finely stranded with core end processing	1 35 mm²		
afety related data			
proportion of dangerous failures with high demand rate according to SN 31920	73 %		
B10 value with high demand rate according to SN 31920	1 000 000		
Electrical Safety			
protection class IP on the front according to IEC 60529	IP20		
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front		
Approvals Certificates			
General Product Approval		For use in hazard- ous locations	Test Certificates



Confirmation







Special Test Certificate

Test Certificates

Marine / Shipping

Type Test Certificates/Test Report











Marine / Shipping

other

Dangerous Good

Environment





Confirmation

Transport Information

Environmental Confirmations

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2155-4JA37-0AK6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2155-4JA37-0AK6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4JA37-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2155-4JA37-0AK6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4JA37-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2155-4JA37-0AK6&objecttype=14&gridview=view1

last modified:	12/15/2020 [-