

21 dB Gain Amplifier, Die

0.4 - 6 GHz



MAAM-011326-DIE

Rev. V3

Features

- Wideband Performance
- Gain: 21 dB @ 3 GHz
- P1dB: 20 dBm @ 3 GHz
- Noise Figure: 1.4 dB @ 3 GHz
- OIP3: 36 dBm @ 3 GHz
- Bias Voltage: 5 V
- Bias Current: 90 mA
- 50 Ω Matched Input / Output
- Positive Voltage Only
- Die Size: 0.59 x 0.70 mm
- RoHS* Compliant

Applications


- Instrumentation & Communication Systems

Description

MAAM-011326-DIE is an easy-to-use, wideband amplifier that operates from 0.4 to 6 GHz. The amplifier provides 21 dB gain, 20 dBm output P1dB and 36 dBm OIP3 at 3 GHz. The gain slope is only ± 0.5 dB from 0.5 to 3 GHz. It is matched to 50 Ω with typical return losses of 15 dB at the input and 13 dB at the output. The amplifier requires only positive bias voltages and consumes 90 mA from a 5 V supply.

MAAM-011326-DIE is suitable for a wide range of applications in instrumentation and communication systems.

Functional Schematic



Pad Configuration^{1,2,3}

Pin #	Pin Name	Function
1	RFIN	RF Input
2	RFOUT / V _{DD}	RF Output / V _{DD}

1. The RFIN pad is DC coupled and matched to 50 Ω . An external DC block is required
2. The RFOUT pad is DC coupled and matched to 50 Ω . DC bias is supplied through this pad.
3. Backside of die must be connected to RF, DC and thermal ground.

Ordering Information

Part Number	Package
MAAM-011326-DIE	Bare Die

* Restrictions on Hazardous Substances, compliant to current RoHS EU directive.

21 dB Gain Amplifier, Die

0.4 - 6 GHz



MAAM-011326-DIE

Rev. V3

Electrical Specifications: $T_B = 25^\circ\text{C}^4$, $V_{DD} = +5\text{ V}^5$, $Z_0 = 50\ \Omega$ (Probe Data with Bias Tees)

Parameter	Test Conditions	Units	Min.	Typ.	Max.
Gain	0.5 GHz	dB	21.0	22.0	—
	2 GHz		—	21.5	
	3 GHz		20.0	21.0	
	4 GHz		—	21.0	
	6 GHz		19.0	20.0	
Gain Variation vs. Temp	0.5 - 3 GHz	dB/°C	—	0.01	—
	3 - 6 GHz			0.02	
Gain Variation vs. Freq	0.5 - 3 GHz	dB	—	±0.5	—
Noise Figure	0.5 GHz	dB	—	1.5	1.8
	3 GHz			1.4	1.6
	6 GHz			2.0	2.2
Input Return Loss	0.5 - 2 GHz	dB	—	-15	-10
	2 - 4 GHz			-16	-11
	4 - 6 GHz			-20	-10
Output Return Loss	0.5 - 6 GHz	dB	—	-13	-12
P1dB	0.5 GHz	dBm	—	20.3	—
	2 GHz			20.3	
	3 GHz			20.0	
	4 GHz			19.0	
	5 GHz			17.6	
	6 GHz			16.2	
Saturated Output Power	0.5 - 6 GHz	dBm	—	21	—
Output IP3 ⁶	0.5 GHz	dBm	33.0	35.0	—
	2 GHz		—	38.0	
	3 GHz		32.5	36.0	
	4 GHz		—	34.0	
	5 GHz		—	31.5	
	6 GHz		27.5	30.0	
Supply Current	Quiescent bias	mA	—	90	100

4. Baseplate temperature.

5. Drain voltage injected through the RF output port using an external bias tees. Voltage at the output pin is $\approx +4.8\text{ V}$.

6. Output IP3 tested with two input tones of -20 dBm each with 10 MHz spacing.

21 dB Gain Amplifier, Die

0.4 - 6 GHz



MAAM-011326-DIE

Rev. V3

Maximum Operating Conditions

Parameter	Rating
Input Power	5 dBm
IC	120 mA
Junction Temperature ^{7,8}	+150°C
Operating Temperature	-40°C to +105°C

7. Operating at nominal conditions with junction temperature $\leq 130^\circ\text{C}$ will ensure MTTF $> 1 \times 10^6$ hours.

8. Junction Temperature (T_J) = $T_B + \Theta_{jc} * (V * I)$

Typical thermal resistance (Θ_{jc}) = 65°C/W .

a) For $T_B = +25^\circ\text{C}$,

$T_J = 55^\circ\text{C}$ @ 5 V, 90 mA

b) For $T_B = +105^\circ\text{C}$,

$T_J = 135^\circ\text{C}$ @ 5 V, 90 mA

Absolute Maximum Ratings^{9,10}

Parameter	Absolute Maximum
V_{DD}	8 V
Input Power	20 dBm
Junction Temperature ¹¹	+150°C
Storage Temperature	-65°C to +125°C

9. Exceeding any one or combination of these limits may cause permanent damage to this device

10. MACOM does not recommend sustained operation near these survivability limits.

11. Junction temperature directly effects device MTTF. Junction temperature should be kept as low as possible to maximize lifetime.

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these HBM Class 1B devices.

21 dB Gain Amplifier, Die 0.4 - 6 GHz




MAAM-011326-DIE


Rev. V3

Typical Performance Curves @ 5 V / 90 mA, $Z_0 = 50 \Omega$ (Probe data with Bias Tees)


Gain




Gain to 10 GHz




Input Return Loss




Output Return Loss



Reverse Isolation



Noise Figure



21 dB Gain Amplifier, Die 0.4 - 6 GHz




MAAM-011326-DIE


Rev. V3

Typical Performance Curves @ 5 V / 90 mA, $Z_0 = 50 \Omega$ (Probe data with Bias Tees)


OIP3 at $P_{IN} = -20$ dBm/tone, 10 MHz Spacing



OIP2 at $P_{IN} = -20$ dBm/tone, 10 MHz Spacing



P1dB




21 dB Gain Amplifier, Die 0.4 - 6 GHz




MAAM-011326-DIE

Rev. V3

Device Assembly¹²



Die Dimensions^{13,14}



Bond Pad Dimensions (μm)

Pad #	Size		Description
	X	Y	
1, 4	100	100	GND
2	100	139	RF _{IN}
3	100	139	RF _{OUT} / V _{DD}

12. DO NOT use eutectic (solder) for die attach. Use electrically and thermally conductive epoxy only, such as Ablestick ABP 8062T.

13. Dimensions are in microns.

14. GND bond pads 1 and 4 are connected to the backside of the die through via holes. These bond pads do not require bond wires. Only pins 2 and 3 require bond wires.

MACOM Technology Solutions Inc. ("MACOM"). All rights reserved.

These materials are provided in connection with MACOM's products as a service to its customers and may be used for informational purposes only. Except as provided in its Terms and Conditions of Sale or any separate agreement, MACOM assumes no liability or responsibility whatsoever, including for (i) errors or omissions in these materials; (ii) failure to update these materials; or (iii) conflicts or incompatibilities arising from future changes to specifications and product descriptions, which MACOM may make at any time, without notice. These materials grant no license, express or implied, to any intellectual property rights.

THESE MATERIALS ARE PROVIDED "AS IS" WITH NO WARRANTY OR LIABILITY, EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHT, ACCURACY OR COMPLETENESS, OR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES WHICH MAY RESULT FROM USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.