SIEMENS

Data sheet 3RA2135-4JA37-0AK6

	Fuseless motor starter Direct start 600VAC Size S2 54-65Amp 110/120VAC
	50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 100 KA Also full fills type Of coordination 1 1NO+1NC (MSP)
	1NO+1NC (contactor)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
 of the supplied contactor 	3RT2037-1AK60
 of the supplied circuit-breakers 	3RV2031-4JA15
 of the supplied link module 	3RA2931-1AA00
General technical data	
size of the circuit-breaker	S2
size of load feeder	S2
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Weight	3.05 kg
Ambient conditions	
ambient temperature	
during operation	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current- dependent overload release	54 65 A
operating voltage	
rated value	
	690 V
at AC-3 rated value maximum	690 V 690 V
at AC-3 rated value maximum operating frequency rated value	
	690 V
operating frequency rated value	690 V 50 60 Hz
operating frequency rated value operational current at AC-3 at 400 V rated value	690 V 50 60 Hz
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	690 V 50 60 Hz 55 A
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	690 V 50 60 Hz 55 A
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control	690 V 50 60 Hz 55 A
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC	690 V 50 60 Hz 55 A 30 000 W
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value	690 V 50 60 Hz 55 A 30 000 W
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37
operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions	690 V 50 60 Hz 55 A 30 000 W 110 V 88 121 V 120 V 96 132 V 16 VA 0.37

UL/CSA ratings			
full-load current (FLA) for 3-phase AC motor			
at 480 V rated value	65 A		
at 600 V rated value	54 A		
yielded mechanical performance [hp]			
for single-phase AC motor			
— at 110/120 V rated value	5 hp		
— at 230 V rated value	10 hp		
• for 3-phase AC motor			
— at 200/208 V rated value	20 hp		
— at 220/230 V rated value	20 hp		
— at 460/480 V rated value	50 hp		
— at 575/600 V rated value	50 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (Iq)	•		
• at 400 V according to IEC 60947-4-1 rated value	100 000 A		
nstallation/ mounting/ dimensions			
mounting position	vertical		
fastening method	Snap-mounted to DIN rail or screw-mounted with additio	nal nush-in lug	
height	274 mm	nai pasii iii lag	
width	55 mm		
depth	150 mm		
required spacing	100 11111		
• for grounded parts			
— forwards	0 mm		
— backwards	0 mm		
— upwards	50 mm		
— at the side	10 mm		
— downwards	10 mm		
• for live parts	10 11111		
— forwards	0 mm		
— backwards	0 mm		
— upwards	50 mm		
— downwards	10 mm		
— at the side	10 mm		
Connections/ Terminals			
type of electrical connection for main current circuit	screw-type terminals		
type of connectable conductor cross-sections for main contacts stranded	1 50 mm², 2x (1 25 mm²)		
connectable conductor cross-section for main contacts finely stranded with core end processing	1 35 mm²		
Safety related data			
proportion of dangerous failures with high demand rate according to SN 31920	73 %		
B10 value with high demand rate according to SN 31920	1 000 000	1 000 000	
Electrical Safety			
protection class IP on the front according to IEC 60529	IP20	IP20	
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front		
Approvals Certificates			
		For use in hazard-	
General Product Approval		ous locations	





Confirmation







Test Certificates Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway Dangerous goods







Confirmation

Special Test Certificate

Transport Information

Environment

Environmental Confirmations

Further information

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2135-4JA37-0AK6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2135-4JA37-0AK6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2135-4JA37-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

 $\underline{\text{http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RA2135-4JA37-0AK6\&lang=en}$

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2135-4JA37-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2135-4JA37-0AK6&objecttype=14&gridview=view1

last modified: 12/15/2020 **©**