

GaAs SPDT Switch, Absorptive, Single or Dual Supply, DC - 4 GHz



MASW-007071

Rev. V7

Features

- Operates DC - 4 GHz on Single or Dual Supply
- ASIC TTL / CMOS Driver
- Low DC Power Consumption
- 50 Ω Nominal Impedance
- Test Boards are Available
- Tape & Reel are Available
- Lead-Free 4 x 6 mm PQFN Package
- RoHS* Compliant Version of SW90-0002

Applications

- Wireless Infrastructure

Description


The MASW-007071 is a single pull double throw (SPDT) absorptive pHEMT switch with integral TTL driver. This device is in a PQFN plastic surface mount package. This switch offers excellent broadband performance and repeatability from DC to 4 GHz, while maintaining low DC power dissipation.

Ordering Information¹

Part Number	Package
MASW-007071-000100	Bulk Packaging
MASW-007071-0001TR	1000 piece reel
MASW-007071-0001TB	Sample Test Board

1. Reference Application Note M513 for reel size information.

Block Diagram (single supply)²



Pin Configuration (single supply)²

Pin #	Function
1, 5, 6, 10, 11, 13, 15, 16, 17, 19, 21, 22, 25, 27, 28, 29	No Connection
2, 4, 7, 9, 30, 32	GND
3	RFC
8	RF1
12, 26	VEE
14, 20	VCC
18	C1
23	CP1
24	CP2
31	RF2

2. See functional schematic for dual supply operation.

* Restrictions on Hazardous Substances, compliant to current RoHS EU directive.

GaAs SPDT Switch, Absorptive, Single or Dual Supply, DC - 4 GHz



MASW-007071

Rev. V7

Electrical Specifications: Freq. = DC - 4 GHz, $T_A = 25^\circ\text{C}$, $Z_0 = 50\ \Omega$

Parameter	Test Conditions	Units	Min.	Typ.	Max.
Insertion Loss	RFC - RF1, RF2 (Logic per truth table)	dB	—	—	1.8
Isolation	RF1 - RF2 (All Logic "0")	dB	30	—	—
VSWR	On (RFC, RF1, RF2), (Logic per truth table) Off (RF1, RF2), (Logic per truth table)	Ratio	—	—	2.0:1 1.8:1
1 dB Compression	50 MHz 0.5 - 4.0 GHz	dBm	—	18 29	—
Input IP_3	Two-tone inputs up to +5 dBm 50 MHz 0.5 - 4.0 GHz	dBm	—	36 46	—
Switching Speed	T_{ON} (50% Control to 10% RF) T_{OFF} (50% Control to 90% RF) T_{RISE} (10% to 90% RF) T_{FALL} (90% to 10% RF)	ns	—	31 19 6 2	—
V_{CC}	—	V	4.5	5.0	5.5
Input Voltage	LOW-level (V_{IL}) HIGH-level (V_{IH})	V	0.0 2.0	—	0.8 5.0
I_{IN} (Input Leakage Current)	$V_{IN} = V_{CC}$ or GND	μA	-1.0	—	1.0
I_{CC}^3	V_{CC} min. to max., Logic "0" or "1"	mA	—	5	12
Turn-on Current ⁴	For guaranteed start-up	mA	—	—	125
ΔI_{CC} (Additional Supply Current Per TTL Input Pin)	$V_{CC} = \text{max.}$, $V_{ctrl} = V_{CC} - 2.1\text{ V}$	mA	—	—	1.0
Switching Noise	Generated from DC-DC Converter with recommended capacitors, 3.5 MHz	dBm	—	-93	—
Thermal Resistance θ_{JC}	—	$^\circ\text{C/W}$	—	15	—

- During turn-on, the device requires an initial start up current (I_{CC}) specified as "Turn-on Current". Once operational, I_{CC} will drop to the specified levels.
- The DC-DC converter is guaranteed to start in 100 μs as long as the power supplies have the maximum turn-on current available for start-up.

Absolute Maximum Ratings^{5,6}

Parameter	Absolute Maximum
Input Power 0.05 GHz 0.5 - 4.0 GHz ⁷	27 dBm 34 dBm
V _{CC}	-0.5 V ≤ V _{CC} ≤ +6.0 V
V _{IN} ⁸	-0.5 V ≤ V _{IN} ≤ V _{CC} + 0.5 V
Operating Temperature	-40°C to +85°C
Storage Temperature	-65°C to +125°C

5. Exceeding any one or combination of these limits may cause permanent damage to this device.
6. MACOM does not recommend sustained operation near these survivability limits.
7. When the RF input is applied to the terminated port, the absolute maximum power is +30 dBm.
8. Standard CMOS TTL interface, latch-up will occur if logic signal is applied prior to power supply.

Truth Table (Switch)

Control Input	Condition of the Switch	
	RF Common to each RF Port	
C1	RF1	RF2
"0" = TTL Low	Off	On
"1" = TTL High	On	Off

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

Moisture Sensitivity

The MSL rating for this part is defined as Level 2 per IPC/JEDEC J-STD-020. Parts shall be stored and/or baked as required for MSL Level 2 parts.

GaAs SPDT Switch, Absorptive, Single or Dual Supply, DC - 4 GHz




MASW-007071

Rev. V7


Functional Schematics:

Single Supply Operation^{9,10,11} $V_{CC} = +5\text{ V}$



Pin #	Function
1, 5, 6, 10, 11, 13, 15, 16, 17, 19, 21, 22, 25, 27, 28, 29	No Connection
2, 4, 7, 9, 30, 32	GND
3	RFC
8	RF1
12, 26	V_{EE}
14, 20	V_{CC}
18	C1
23	CP1
24	CP2
31	RF2

Dual Supply Operation^{11,12} $V_{CC} = +5\text{ V}$, $V_{EE} = -3.3\text{ V to } -8\text{ V}$







Pin #	Function
1, 5, 6, 10, 11, 13, 15, 16, 17, 19 - 29	No Connection
2, 4, 7, 9, 30, 32	GND
3	RFC
8	RF1
12	V_{EE}
14	V_{CC}
18	C1
31	RF2

12. Dual Supply Operation will eliminate the start-up current mentioned in note 3. It will also eliminate spurious signals caused by the DC-DC converter that are present in single supply operation.

9. V_{EE} is internally generated and must remain isolated from external power supplies. Generated noise is typical of switching DC-DC Converters.
10. Connections and external components shown in functional schematic are required. Capacitors (0.1 μF) need to be located near pins 20 & 26.
11. The exposed pad centered on the package bottom must be connected to RF and DC ground. (For PQFN Packages).

Typical Performance Curves

Insertion Loss

Isolation

On VSWR

Off VSWR (Terminations)


Rev. V7

0.398
 .016
 RF2
 0.46
 .018
 30X 0.711
 .028
 0.343
 .014
 PIN 1
 PIN 1 MARKER
 RFC
 2.815
 .111
 2.779
 .109
 30X 0.279
 .011
 6X 45° CHAMFER
 ON PAD
 RF1
 4.763
 .188
 6.604
 .260

CIR
 DIP
 RF
 GR
 RF
 01 μ F +
 01 μ F +
 01 μ F +

CIRCUIT MATERIAL: TETRA II .010 INCH THICK
DIELECTRIC CONSTANT 4.4
RF LINES ARE COPLANER- USE GND SPACING OF .016
GROUND VIAS .014
RF PORTS ARE 50 OHMS
01 μ F +10% CAPACITOR REQUIRED BETWEEN PINS 23 AND 24
01 μ F +10% BYPASS CAPACITOR REQUIRED ON Vcc TRACE NEAR PIN 20
01 μ F +10% BYPASS CAPACITOR REQUIRED ON Vee TRACE NEAR PIN 26

The technical drawing illustrates the dimensions of a 32-pin DIP package. The top view (left) shows the package layout with labels for the PIN #1 IDENTIFIER, PART NUMBER (.2362 ±.0006), LOT NUMBER (U2), DATE CODE, LOT NUMBER (U3), and LOT NUMBER (U1). The side view (right) shows the package profile with dimensions for the EXPOSED PAD, SEATING PLATE, and various pin dimensions. Dimensions are provided in inches and millimeters.

Top View Dimensions:

- PIN #1 IDENTIFIER: .0155in/0.39mm X 45 DEG. CHAMFER
- PART NUMBER: .2362 ±.0006
- LOT NUMBER (U2): .1575 ±.004
- DATE CODE: .1575 ±.004
- LOT NUMBER (U3): .1575 ±.004
- LOT NUMBER (U1): .1575 ±.004
- Pin 1: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 2: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 3: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 4: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 5: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 6: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 7: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 8: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 9: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 10: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 11: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 12: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 13: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 14: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 15: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 16: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 17: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 18: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 19: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 20: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 21: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 22: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 23: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 24: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 25: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 26: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 27: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 28: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 29: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 30: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 31: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 32: .0155in/0.39mm X 45 DEG. CHAMFER

Side View Dimensions:

- EXPOSED PAD: .00354 ±.00039
- SEATING PLATE: .0020 ±.0000
- Pin 1: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 2: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 3: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 4: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 5: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 6: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 7: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 8: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 9: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 10: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 11: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 12: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 13: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 14: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 15: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 16: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 17: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 18: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 19: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 20: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 21: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 22: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 23: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 24: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 25: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 26: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 27: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 28: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 29: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 30: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 31: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 32: .0155in/0.39mm X 45 DEG. CHAMFER

Bottom View Dimensions:

- Pin 1: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 2: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 3: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 4: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 5: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 6: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 7: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 8: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 9: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 10: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 11: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 12: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 13: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 14: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 15: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 16: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 17: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 18: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 19: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 20: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 21: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 22: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 23: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 24: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 25: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 26: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 27: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 28: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 29: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 30: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 31: .0155in/0.39mm X 45 DEG. CHAMFER
- Pin 32: .0155in/0.39mm X 45 DEG. CHAMFER

[†] Reference Application Note M538 for lead-free solder reflow recommendations. Reference Application Note S2083 for PCB footprint information.

MACOM Technology Solutions Inc. ("MACOM"). All rights reserved.

These materials are provided in connection with MACOM's products as a service to its customers and may be used for informational purposes only. Except as provided in its Terms and Conditions of Sale or any separate agreement, MACOM assumes no liability or responsibility whatsoever, including for (i) errors or omissions in these materials; (ii) failure to update these materials; or (iii) conflicts or incompatibilities arising from future changes to specifications and product descriptions, which MACOM may make at any time, without notice. These materials grant no license, express or implied, to any intellectual property rights.

THESE MATERIALS ARE PROVIDED "AS IS" WITH NO WARRANTY OR LIABILITY, EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHT, ACCURACY OR COMPLETENESS, OR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES WHICH MAY RESULT FROM USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.