

www.lemo.com

EGG.2K.P12.CLL

SUMMARY

Wires

Low voltage 4
Fluidic 1

Series 2K

Termination type Female solder

IP rating 68

AWG wire size 0.00 - 0.00

Cable Ø 0.00 - 0.00 mm

Status active

Matching parts FGG.2K.P12.CLAC65



Image is for illustrative purpose only

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model EG*: Fixed receptacle, nut fixing

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Weight 35.79 g

Performance

Configuration 2K.P12: 1 Fluidic with valve P1, 4 Low Voltage

Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 6 Amps

Specifications

Contact Type: Solder

Max pressure: 6 bar (87.02 psi)
Tube Inner Dia.: 1.8 mm (0.070)
Tube Outer Dia.: 3.0 mm (0.118 in.)

Test voltage (kV rms) Contact-contact: 0.85 Test voltage (kV rms) Contact-shell: 1.2

Others


LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.


Endurance (Shell): 5000 mating cycles Temp (min / max): -55°C / +200°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 95 dB (10 MHz) Shielding (min): 80 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS







Dimensions

	А	В	Е	L	М	N	S1	S 3	e
mm.	25	27.5	9	30.7	5	28.6	18.5	24	M20x1.0
in.	0,98	1,08	0,35	1,21	0,20	1,13	0,73	0,94	

RECOMMENDED BY LEMO

Tools

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

