# MSKSEMI 美森科







TVS



TSS



MOV



GDT



PIFF

## **MSOP07DRZ-REEL**

产品手册





#### 概述


MSOP07DRZ-REELR 是一个高精密运算放大器,其最大失调电压控制在150uV。增益达200V/mV。因此MSOP07DRZ-REEL 特别适合用仪表等方面。

MSOP07DRZ-REEL 有着较宽的输入电压范围( $\pm 13V$ ), 以及高达100dB以上的共模抑制比(CMRR), 其在高闭环增益电路中亦保持出色的线性度和增益精度。


## 主要特点

- 最大失调电压. 150uV MAX
- 低失调电流 Iio=1.3nA typ
- 工作电压范围宽 ±3V to ±20V

#### 引脚描述和标记




## 输入失调调零电路





## 框图



## 极限参数 (绝对最大额定值, 若无其它规定, Tamb=25℃)

参数名称	符号	数值	单位
电源电压	Vcc	±20	V
输入电压	Vi	±18	V
输入差动电压	Vid	±30	V
工作温度	Topr	-10 <sup>~</sup> +85	$^{\circ}$
贮存温度	Тѕтс	-40 <sup>~</sup> +150	$^{\circ}$


## **电特性**(Vcc=±15V, Tamp=25℃ 特殊情况另外说明)

A-4- 1-1	描述	数 值			単位
符号	打 号		典型值	最大值	半世
Vio	失调电压			150	uV
V10	0°C <tamb<70°c< td=""><td></td><td></td><td>250</td><td>uV</td></tamb<70°c<>			250	uV
DVio	失调温度漂移			1.8	uV/℃
Iio	输入失调电流			8	nA
Iib	输入偏置电流			28	nA
Viom	输入共模电压	±13	⊥19 E		V
Vicm	0°C <tamb<70°c< td=""><td>±13</td><td><math>\pm 13.5</math></td><td></td></tamb<70°c<>	±13	$\pm 13.5$		
CMR	共模抑制比	100			dB
SVR	电源抑制比	90			dB
Avd	Large Signal Voltage Gain VCC =±15V, RL= 2kΩ, VO=±10V,	100			V/mV




Vopp	输出峰值 RL = 10kΩ RL = 2kΩ	±12 ±11.5			V
GBP	增益带宽 RL = 2kΩ, CL= 100pF, f = 100KHz)		0. 5		MHz
ICC	电源电流(no load) 0℃ <tamb <70℃<br="">VCC = ±3V</tamb>		3.8	6 7 3	mA

## 典型应用图




高稳定热电偶放大





精密绝对值电路



## 封装图 (SOP-8)







<b>加</b> . 口.	毫米(mm)		英寸(Inch)		
符号	最小值	最大值	最小值	最大值	
Α	1.350	1.750	0.053	0.069	
A1	0.100	0.250	0.004	0.010	
A2	1.350	1.550	1.550	0.061	
b	0.330	0.510	0.013	0.020	
С	0.170	0.250	0.006	0.010	
D	4.700	5.100	0.185	0.200	
E	3.800	4.000	0.150	0.157	
E1	5.800	6.200	0.228	0.244	
е	1.27(BSC)		0.050(BSC)		
L	0.400	1.270	0.016	0.050	

## 订货信息

料号	封装	包装
MSOP07DRZ-REEL	SOP8	2500PCS



#### **Attention**

- Any and all MSKSEMI Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your MSKSEMI Semiconductor representative nearest you before using any MSKSEMI Semiconductor products described or contained herein in such applications.
- MSKSEMI Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all MSKSEMI Semiconductor products described or contained herein.
- Specifications of any and all MSKSEMI Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer'sproducts or equipment.
- MSKSEMI Semiconductor. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with someprobability. It is possiblethat these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits anderror prevention circuitsfor safedesign, redundant design, and structural design.
- In the event that any or all MSKSEMI Semiconductor products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from theauthorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of MSKSEMI Semiconductor.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. MSKSEMI Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. Whendesigning equipment, referto the "Delivery Specification" for the MSKSEMI Semiconductor productthat you intend to use.