ISO9001: 2000	ISO14001: 2004

Title.	TACT SWITCH
Product Model.	TS-1003
Customer's Part	NO.
Customer's M	odel:

Customer's Approval Requested.

Please return this copy as a certification of yourapproval.

Checked by: Date:

Approved by: Date:


APPROVE	REVIEW	POLT
王凱	李成功	許志明


XUNPU ELECTRONICS CO.,LTD




CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		TS-1003	TACT SWITCH	


产品符合ROHS






PCB Layout(Pattern side)







General tolerance: ±0.2mm

NO.	NAME	MATERIAL	NATIONALITY	QTY.	FINISHING
1	Terminal	Brass		4	Plating silver
2	Contact	SUS		1	
3	Cover	SPCC		1	PLAting nickel
4	Base	Nylon		1	Black
5	Keystoke	Nylon		1	BlacK

APPROVE BY	王凯12.05.21	CHECKED BY	李成功12.05.21	PRPARE BY	许志明12.05.21
------------	------------	------------	-------------	-----------	-------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		TS-1003	TACT SWITCH	

A.Specification & meanings

The name of the tact switch is composed by type and specification, the particular meaning of the type, specification and code is as follows.

TS-1003− □□□	
	Operating force (refer to chart 2)
	 Product height (refer to chart 1)

1. Product height: It is denoted by three figures:

Code	Product height(mm)	Code	Product height(mm)	Code	Product height(mm)
043	4.3	090	9.0	140	14.0
045	4.5	095	9.5	145	14.5
050	5.0	100	10.0	150	15.0
055	5.5	105	10.5	155	15.5
060	6.0	110	11.0	160	16.0
065	6.5	115	11.5	165	16.5
070	7.0	120	12.0	170	17.0
075	7.5	125	12.5	175	17.5
080	8.0	130	13.0	180	18.0
085	8.5	135	13.5	185	18.5

2. Operating force: An English letter expresses it, unite: Newton (N),as chart 2 shows:

Operating			5 4	
force Spec		Press force(N)	Return force	
16	1.6	1.6±0.5	0.4min	
26	2.6	2.6±0.5	0.4min	

Examples: "TS-1003-04316" denotes the ta ct switch with 12×12 base, the height is 4.3 mm, the stem is black, the operating force is 1.6 N.

APPROVE BY	王凱12.05.21	CHECKED BY	李成功12.05.21	PRPARE BY	許志明12.05.21
------------	------------	------------	-------------	-----------	-------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		TS-1003	TACT SWITCH	

1、 概述

GENERAL

1.2 适用范围

APPLICATION

此规格书适用于机械式轻触开关的相关要求

This specification is applied to the requirements for TACTILE SWITCH (MECHANICAL CONTACT)

1.3 工作温度范围

Operating Temperature Range

- -20℃~70℃(在标准大气压、标准湿度条件下)
- -20°C ~70°C (Normal humidity, normal air pressure)
- 1.4 贮藏温度范围

Storage Temperature Range

- -30℃~80℃(在标准大气压、标准湿度条件下)
- -30 $^{\circ}$ C $^{\circ}$ 80 $^{\circ}$ C (Normal humidity, normal air pressure)
- 1.5 测试条件

Test Conditions

在没有其它特定的条件下,应该在以下的条件下进行测试和测量:

Unless otherwise specified, tests and measurement shall be made in the following standard conditions:

常温......5℃~**35**℃

Normal temperature......5°C ~35°C

标准湿度......相对湿度 25%~85%

Normal humidity.....relative humidity 25%~85%

标准大气压......86KPa~106Kpa

Normal air pressure......86Kpa~106Kpa

在制造过程中,测试和测量应该在以下的条件下进行:

If any doubt arise from the judgment, tests shall be conducted at the following conditions:

温度......20℃±2℃ Temperature......20℃±2℃

相对湿度......65%±5%

Relative humidity......65%±5%

环境气压......86KPa~106Kpa

Airpressure......86KPa~106Kpa

APPROVE BY	王凱12.05.21	CHECKED BY	李成功12.05.21	PRPARE BY	許志明12.05.21
------------	------------	------------	-------------	-----------	-------------



CUSTOMER	CUSTOMER'S P/N	GYE'S P/N	PRODUCT	REVISION
		TS-1003	TACT SWITCH	

2、 详细说明

Detailed specification

2.1 外观:应无影响、降低产品性能的缺陷;

Appearance: There should be no defects that affect the serviceability of product.

2.2 结构尺寸和安装尺寸:应符合装配图要求;

Style and dimension: shall conform to the assemble drawings.

2.3 操作形式:有触觉反应的操作

Type of actuating: Tactile feedback.

2.4 开关结构: 单回路单输出(具体的触点结构在装配图中已绘出);

Contact arrangement: 1 pole, 1 throw

(Details of contact arrangement are given in the assembly drawings.)

2.5 开关工作额定值: DC 12V, 50mA (有效值)

Ratings: 12V DC, 50mA (effective value)

3. 电气性能:

ELECTRICAL SPECIFICATION

项	目		试验条件		要求		
ITI	EM	Ti	TEST CONDITIONS				
		的电路中,以一个等于		加于手柄中心			
1	接触电阻		load of 2 times ope		≤100mΩ		
	Contact Resistance	the center of the stem	n, measurements sh	all be made by			
		5V DC 10mA or me	ore than 1KHZ AC	small-current			
		contact resistance me	ter.				
2	绝缘电阻 Insulation Resistance	子之间底座、盖板的电 Measurement sha 100V DC potential,	在端子之间施加 DC 100V /1min 的条件下,测量端子之间底座、盖板的电阻值 Measurement shall be made following application of 100V DC potential, across terminals, and across terminals and cover, for one minute.				
	介质耐压	在端子之间施加 2	250V AC(50HZ 或 60	0HZ)/1min	无击穿、无飞弧		
3	Dielectric	250V AC (50HZ c	or 60HZ) shall be app	olied across	There should be		
	voltage proof	terminals, for one	,		no breakdown and		
	voltage proof	, , , , , ,	flashover				
APPROVE	王凱12.05.2	1 CHECKED BY	李成功12.05.21	PRPARE B	Y 許志明12.05.21		



CUSTOMER		CUSTOMER'S P/N	GYE'S		REVISION		
			TS-10	003	TACT SWIT	СН	
	项目		试验条	件			要求
	ITEM		TEST CONDIT	ΓIONS		REC	QUIREMENTS
	械性能: IANICAL SPEC						
据力Operating Force Type Type Type Type Type Type Type Typ						s e re	fer to chart 3
2	最大行程 Full Travel 开关垂直于操作方向放置,以一个等于 2 倍按力的静负荷施加在 开关驱动件顶端中心,测量顶端移动的距离。 Placing the switch such that the direction of switch operation is vertical and then applying static load of 2times operating force to the center of the stem; the travel distance for the switch to come to a stop shall be measured.					S 0	.25±0.1mm
APP	ROVE BY	王凱12.05.21 CHE	CKED BY	李成功12.0	5.21 PRPA	RE BY	許志明12.05.21



		7111 0	/ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \	ALL NOVAL OF LOTTOAT				
С	USTOMER	CUSTOMER'S	P/N GYE	.'S P/N	PRODUC1	-	REVISION	
			TS-	1003	TACT SWIT	СН		
	项目		试验 第	条件			要求	
	ITEM		TEST CONI	DITIONS		RE	QUIREMENTS	
3	回弹力 Return Force	to the whole trav	自由位置转换的力度 ch is installed so ical and upon de el distance, the f ll be measured.	h ro er es	efer to chart 3			
4	停止强度 Stop Streng	开关垂直于操作力 荷持续 1min。 Placing the switc vertical, and the direction of stem	ch such that the n a static load	s e There	机械和电气损坏 shall be no sign of e mechanically and electrically.			
5	手柄拔出强度 Stem Strength	开关垂直于操作为 的行程范围。 Placing the switc vertical, and ther opposite to the d	ch such that the n the maximum f	s	20N.min.			
6	在以下设定条件下进行测量: Measurements shall be made following the test set forth below: (1) 焊接温度:245±5℃ Solder temperature: 245±5℃ (2) 浸入时间:2s±0.5s Immersion time: 2s±0.5s 对于其它步骤参考《GB 5095.6—86》试验12a The other steps please refer to 《GB 5095.6-86》TEST 12a						外涂层应均匀覆盖 上 for the edge, the should cover a m 90%	
APP	ROVE BY	王凱12.05.21	CHECKED BY	李成功12.	05.21 PRPA	ARE BY	許志明12.05.21	



		J 1 1 1			/ \1 1 1	NOVA			<u> </u>	10110
С	USTOMER		CUSTOMER'	S P/N	GYE'	S P/N	PR	ODUCT		REVISION
					TS-1	003	TAC	T SWITCH	1	
	项目 试验条件									要求
ITEM TEST C						IDITIONS			RE	QUIREMENTS
	5、极限电气性能: ENVIRONMENTAL SPECIFICATION									
1	样品应按照以下实验条件进行测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试: Following the test set forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made: (1) 温度: -30±2℃ Temperature: -30±2℃ (2) 时间: 96h Time: 96h							Contac ≤200m 项目 3,4		
2	高温测试 Heat resista	ance	标准湿度的 forth below humidity con (1) 温度 tem (2) 时间	temperature:80±2℃ 项目						
根据下面的测试要求进行 5 次循环的温度周期性测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试。测试期间样品应保持干燥. After 5 cycles of following conditions, the sample shall be allowed to stand under normal temperature and humidity conditions for 1 h. and measurements shall be made. During the test water drops shall be removed. Temperature Time								Ω 4.1,4.2,4.3		
APP	PROVE BY	王豈	<u> </u> 凯12.05.21	CHE	CKED BY	李成功12.	05.21	PRPARE	BY	許志明12.05.21



С	USTOMER	CI	USTOMER'S		GYE'S	S P/N		RODUCT		REVISION
					TS-1	003	TAC	CT SWITC	Н	
	项目				试验》	条件				要求
	ITEM			TES	ST CON	DITIONS			RE	QUIREMENTS
4	湿温测试 Moisture resistanc		样品应按照以下实验条件进行测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试: Following the test set forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made: (1) 温度: 60±2℃ temperature: 60±2℃ (2) 相对湿度: 90%~95% relative humidity:90% to 95% (3) 时间: 96h time: 96h						接触电 Contac ≤200m 项目3,	
5	硫化试验 Sulfuratio resistanc); 1 1	样品应按照以下实验条件进行测试,实验后样品应放在常温及标准湿度的环境中 1 小时后做性能测试: Following the test set forth below the sample shall be left in normal temperature and humidity conditions for 1 h before measurements are made: (1) H2S气体浓度: 3ppm±1ppm H ₂ S gas concentration: 3ppm±1ppm (2) 时间: 72h Time: 72h (3) 温度: 40±2℃(90~95%RH) temperature: 40±2℃(90~95%RH)					接触电 Contac ≤200m 项目3,		
6	盐雾试验 Salt Mist	t :	在以下设定条件下进行测量: The switch shall be checked after following test: (1) 温度: 35℃±2℃ temperature: 35℃±2℃ (2) 盐溶液浓度: 5±1% (质量百分比) salt solution: 5±1%(solids by mass) (3) 时间: 8h±1h Time: 8h±1 hour 实验后的盐沉积物后水冲掉 After test, salt deposit shall be removed by running water.					corrosi	上没有腐蚀斑点 No remarkable on shall be ized in metal part.	
APP	ROVE BY	 王凱 <i>'</i>	12.05.21	CHECKE	D BY	李成功12.0	05.21	PRPAR	E BY	許志明12.05.21



					<i>,</i> ,, , ,					
С	CUSTOMER		CUSTOMER'S	TOMER'S P/N GYE'S P/N PRODUCT		RODUCT	REVISION			
					TS-1	1003	TAC	CT SWITCH		
	限机械性能:									
Е	NDURANCE	SPEC	IFICATION) D = 7A					
	项目				试 验	条 件				要求
	ITEM TEST CONDITIONS							RE	QUIREMENTS	
1	工作寿 _行 Operatior	•	DC 12 (2) 按动词 Rate (3) 按力: Operat	nt shall b 2V,50m 2V,50 m 速率:1 秒 of opera :按力的 ing Force 无故障寿	ne made fol nA 带负载 nA resistive 欠/秒 ation: 1time J 1.5 倍 e: Oper	load	.5double life 欠	接 re 舰 (大 O in 项	esistar 点点弹 Conta D : 不 perati itial va 〔目 3,4	I≤200mΩContact nce≤200mΩ 力≤10ms ct bounce≤10ms按 闭 值 的 ±30% ng Force: alue±30% I.1,4.2,4.3 I.1,4.2,4.3
2 相	振动Vibra 接条件:	ition	Measuremer (1)振动线 Vibi (2)振幅 Amp 振动 Diredire ④ 测试	Vibration frequency range: 10 to 55 to 10Hz (2) 振幅(峰一峰): 1.5mm Amplitude: 1.5mm 振动方向: 包括手柄行程方向在内的三个相互垂直的方向 Direction of vibration:Three mutually perpendicular direction including the direction of stem travel						1.1,4.2,4.3 4.1,4.2,4.3
	安宏什: ERING CON	וחודוחו	NS:							
		.5.110	1	加工名						
			请按以下条件进行焊接: (1) 焊锡温度: ≤350℃							
7 4	手工焊接		(2)	连续焊持	妾时间: ≤3	3 s				
7.1	Hand sold	Hand soldering		Please practice according to below conditions: (1) Soldering temperature: 350°C Max. (2) Continuous soldering time: 3 sMax.						
APP	ROVE BY	王豊	Л12.05.21	CHEC	KED BY	李成功12.0	05.21	PRPARE E	3Y	許志明12.05.21
										•



CUSTOMER		CUSTOMER'S P/N	GYE'S P/N		PRODUCT	REVISION		
	TS				TACT SWITCH			
	自动浸焊	项目 Items		条件 Condition				
	Conditions for 助焊剂附着量			不附着于零部件贴装面的程度				
	Auto-dip	Flux built-up		Mounting surface should not be coated with flax				
		预热温度		印刷电路板焊接面的周围温度 100℃ max.				
		Preheating tempera	ature	Ambient tem _l 100℃ max.	surface of PC board.			
7.2		预热温度时间 Preheating tim			60s max.			
		焊接温度			260℃ max.			
		Soldering temp 焊接浸渍时间	perature					
		Continuous dipping	g time	5s max.				
		焊接次数			2次以下			
		Number of solde	ering	2times max.				
	捏接说明.							

焊接说明:

1、开关浸焊后,注意不要用溶剂清洗。

After switches were soldered please be careful not to clean switches with solvent.

1.1 在使用烙铁的情况下,焊锡温度应在350℃以下、3 秒以内。

In the case of using solding iron, solding conditions shall be 350 ℃ max and 3 sec.max.

1.2 浸焊后,注意不要在顶部施加负荷。

Right after switches were soidered; please be careful not to load to on the knobs of switches.

- 2、设计中应注意的事项(Design instructions)
- 2.1 印刷基板的安装孔尺寸参见产品图。

Follow recommended P.W.B. piercing plan in outside drawing page.

- 3、注意点(Note):
- 3.1 注意不要施加超负荷的压力或晃动开关。

Please be cautions not to give excessive static load or shock to swiches.

3.2 开关浸焊后,印刷基板注意不要叠放。

Please be careful not to pile up P.W.B.after switches were soldered.

3.3 保管时尤其应注意避开高湿高温和有腐蚀性气体的环境。如需要长时间保存,请不要打开包装箱。

Preservation under high temperature and high high humidity or corrosive gas should be avoided Especially . When you need to preserve for a long period ,do not open the carton.

APPROVE BY	王凱12.05.21	CHECKED BY	李成功12.05.21	PRPARE BY	許志明12.05.21