

DLW5BSM191SQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5BSM191SQ2# from the official website of Murata Manufacturing Co., Ltd.

Packaging Information

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM191SQ2%23

"#" indicates a package specification code.

In Production RoHS REACH

< List of part numbers with package codes > DLW5BSM191SQ2B DLW5BSM191SQ2K

DLW5BSM191SQ2L



Appearance & Shape





Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
K	330mm Embossed Tape	1500
L	180mm Embossed Tape	400



Other Usage

For general

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





DLW5BSM191SQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5BSM191SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM191SQ2%23

"#" indicates a package specification code.



DLW5AH/5BS series is a high performance wound type chip common mode choke coil.

Features

- 1. High impedance (max. of 4000ohm at 100MHz: DLW5AH) enables great noise suppression.
- 2. Large rated current (max. of 5A) is suitable for power line use.
- DLW5AH/BS series does not damage high speed signal due to high coupling common mode choke coil structure.
- 4. Automatic mounting can be applied.

Applications

- 1. DC power lines in AC adapters of Portable equipment
- 2. DC power lines of DC-DC converters, battery chargers

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

- without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.



DLW5BSM191SQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5BSM191SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM191SQ2%23

"#" indicates a package specification code.



Specifications

Shape	SMD
Size Code (in mm)	5050
Size Code (in inch)	2020
Length	5.0mm
Length Tolerance	±0.3mm
Width	5.0mm
Width Tolerance	±0.3mm
Thickness	4.5mm
Thickness Tolerance	max.
Common Mode Impedance (at 100MHz)	190Ω
Common Mode Impedance (at 100MHz) Tolerance	(Тур.)
Common Mode Impedance (at 10MHz)	19Ω
Common Mode Impedance (at 10MHz) Tolerance	min.
Rated Current	5A
Derating of Rated Current	Yes (Over 75°C) *For details, please check the derating diagram.
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	0.02Ω
DC Resistance	0.02Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.3g

Number of Circuit	1	
Operating Temperature Range(Self-temperature rise is included)	No	

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Product Search Data Sheet

DLW5BSM191SQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW5BSM191SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM191SQ2%23

"#" indicates a package specification code.





Impedance-Frequency Characteristics

In operating temperature exceeding +75°C, derating of current is necessary for DLW5BSM191SQ2. Please apply the derating curve shown in chart according to the operating temperature.



Derating of Rated Current



Impedance-Frequency Characteristics (Main Items)



Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

