SIEMENS

Data sheet

3SU1153-0AB30-1BA0-Z Y12



Illuminated pushbutton, 22 mm, round, metal, shiny, yellow, pushbutton, flat, momentary contact type, with holder, 1NO, LED module with integrated LED 110 V AC, screw terminal, with laser labeling, lower case

| product brand name | SIRIUS ACT | |
|--|---|--|
| product designation | Illuminated pushbuttons | |
| design of the product | Complete unit | |
| product type designation | 3SU1 | |
| product line | Metal, shiny, 22 mm | |
| manufacturer's article number | | |
| of supplied contact module at position 1 | <u>3SU1400-1AA10-1BA0</u> | |
| of supplied LED module | <u>3SU1401-1BC30-1AA0</u> | |
| of the supplied holder | <u>3SU1550-0AA10-0AA0</u> | |
| of the supplied actuator | <u>3SU1051-0AB30-0AA0</u> | |
| number of command points | 1 | |
| Actuator | | |
| design of the actuating element | Button, flat | |
| principle of operation of the actuating element | momentary contact type | |
| product extension optional light source | Yes | |
| color of the actuating element | yellow | |
| material of the actuating element | plastic | |
| shape of the actuating element | round | |
| outer diameter of the actuating element | 29.45 mm | |
| marking of the actuating element | Customized labeling, text in lower case letters | |
| number of contact modules | 1 | |
| Front ring | | |
| product component front ring | Yes | |
| design of the front ring | Standard | |
| material of the front ring | Metal, high gloss | |
| color of the front ring | silver | |
| Holder | | |
| material of the holder | Plastic | |
| Display | | |
| number of LED modules | 1 | |
| General technical data | | |
| product function positive opening | No | |
| product component light source | Yes | |
| insulation voltage rated value | 320 V | |
| degree of pollution | 3 | |
| type of voltage of the operating voltage | AC/DC | |
| surge voltage resistance rated value | 4 kV | |
| protection class IP | IP66, IP67, IP69(IP69K) | |
| • of the terminal | IP20 | |

| degree of protection NEMA ration | |
|--|--|
| degree of protection NEMA rating shock resistance | 1, 2, 3, 3R, 4, 4X, 12, 13 |
| | cinucoidal balf wave 15a / 11 ma |
| e according to IEC 60068-2-27 vibration resistance | sinusoidal half-wave 15g / 11 ms |
| according to IEC 60068-2-6 | 10 500 Hz; 5a |
| | 10 500 Hz: 5g 3 600 1/h |
| operating frequency maximum | 3 000 000 |
| mechanical service life (switching cycles) typical | |
| electrical endurance (switching cycles) typical | 10 000 000 |
| thermal current | 10 A |
| reference code according to IEC 81346-2 | S |
| continuous current of the C characteristic MCB | 10 A; for a short-circuit current smaller than 400 A |
| continuous current of the quick DIAZED fuse link | 10 A |
| continuous current of the DIAZED fuse link gG | 10 A |
| Substance Prohibitance (Date) | 10/01/2014 |
| operating voltage | |
| • at AC | |
| — at 50 Hz rated value | 5 500 V |
| — at 60 Hz rated value | 5 500 V |
| • at DC rated value | 5 500 V |
| Power Electronics | |
| contact reliability | One maloperation per 100 million (17 V, 5 mA), one maloperation per 10 |
| | million (5 V, 1 mA) |
| Supply voltage | |
| type of voltage of the supply voltage of the light source | AC |
| supply voltage of the light source at AC | |
| • at 50 Hz rated value | 110 V |
| at 60 Hz rated value | 110 V |
| Control circuit/ Control | |
| inrush current of LED module maximum | 3 A |
| Auxiliary circuit | |
| | |
| | Silver allow |
| design of the contact of auxiliary contacts | Silver alloy |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts | 0 |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts | |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals | 0 1 |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection | 0 1 screw-type terminals |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories | 0 1 |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections | 0 1 screw-type terminals Screw-type terminal |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 2x (1,1 1,5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • finely stranded with core end processing • finely stranded without core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded with core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) 2x (1,0 1,2 N·m |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded with core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) 1.5 mm ²) 2x (1,0 1,5 mm ²) 1.5 m ² (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 1.5 m ² (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 1.5 m ² (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 1.5 m ² (1,0 1,5 mm ²) 2x (1,0 1,5 m ² (1,0 1,5 mm ²) 2x (1,0 1,5 m ² (1,0 1,5 m ²) 2x (1,0 1,5 m ² (1,0 1,5 m ²) 1.5 m ² (1,0 1,5 m ² (1,0 1,5 m ²) 1.5 m ² (1,0 1,5 m ² (1,0 1,5 m ²) 1.5 m ² (1,0 1,5 m ² (1,0 1,5 m ²) 1.5 m |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded with core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded with core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (0.5 1.5 mm ²) 2x (1,0 1,5 mm ²) 2x (1,0 1,5 mm ²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/Terminals type of electrical connection of modules and accessories type of connectable conductor cross-sections solid with core end processing solid without core end processing finely stranded with core end processing at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature during operation during storage | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C -40 +80 °C |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/Terminals type of electrical connection of modules and accessories type of connectable conductor cross-sections solid with core end processing solid without core end processing finely stranded with core end processing at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature during operation during storage environmental category during operation according to IEC 60721 | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1.5 mm ²) 2x (1,0 1,5 mm ²) 2x (|
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation • during storage environmental category during operation according to IEC 60721 Installation/ mounting/ dimensions | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (1.0 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel) |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation • during storage environmental category during operation according to IEC 60721 Installation/ mounting/ dimensions fastening method | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1,5 mm ²) 2x (1.8 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel) front plate mounting |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation • during storage environmental category during operation according to IEC 60721 Installation/ mounting/ dimensions fastening method • of modules and accessories | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1.5 mm ²) 2x (1,0 1,5 mm ²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel) front plate mounting Front plate mounting Front plate mounting |
| design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Connections/ Terminals type of electrical connection • of modules and accessories type of connectable conductor cross-sections • solid with core end processing • solid without core end processing • finely stranded with core end processing • finely stranded without core end processing • at AWG cables tightening torque of the screws in the bracket tightening torque with screw-type terminals Lamp type of light source color of the light source light intensity Ambient conditions ambient temperature • during operation • during storage environmental category during operation according to IEC 60721 Installation/ mounting/ dimensions fastening method | 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1.5 mm ²) 2x (1.0 1,5 mm ²) 2x (1.8 14) 1 1.2 N·m 0.8 0.9 N·m LED yellow 900 1 400 mcd -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel) front plate mounting |

| shape of the installation opening | round |
|---|---------|
| mounting diameter | 22.3 mm |
| positive tolerance of installation diameter | 0.4 mm |
| mounting height | 11 mm |
| installation width | 29.5 mm |
| installation depth | 49.7 mm |
| Certificates/ approvals | |
| Eurthor information | |

Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10 Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3SU1153-0AB30-1BA0-Z Y12

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3SU1153-0AB30-1BA0-Z Y12

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3SU1153-0AB30-1BA0-Z Y12

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3SU1153-0AB30-1BA0-Z Y12&lang=en

last modified:

1/26/2022 🖸