National Semiconductor is now part of

Texas Instruments.

Search <u>http://www.ti.com/</u> for the latest technical

information and details on our current products and services.

DS90LV017A LVDS Single High Speed Differential Driver



DS90LV017A LVDS Single High Speed Differential Driver General Description Features

The DS90LV017A is a single LVDS driver device optimized for high data rate and low power applications. The DS90LV017A is a current mode driver allowing power dissipation to remain low even at high frequency. In addition, the short circuit fault current is also minimized. The device is designed to support data rates in excess of 600Mbps (300MHz) utilizing Low Voltage Differential Signaling (LVDS) technology.

The device is in a 8-lead small outline package. The DS90LV017A has a flow-through design for easy PCB layout. The differential driver outputs provides low EMI with its typical low output swing of 355 mV. The DS90LV017A can be paired with its companion single line receiver, the DS90LV018A, or with any of National"s LVDS receivers, to provide a high-speed point-to-point LVDS interface.

- >600 Mbps (300 MHz) switching rates
- 0.3 ns typical differential skew
- 0.7 ns maximum differential skew
- 1.5 ns maximum propagation delay
- 3.3V power supply design
- ±355 mV differential signaling
- Low power dissipation (23 mW @ 3.3V static)
- Flow-through design simplifies PCB layout
- Interoperable with existing 5V LVDS devices
- Power Off Protection (outputs in high impedance)
- Conforms to TIA/EIA-644 Standard
- 8-Lead SOIC package saves space
- Industrial temperature operating range (-40°C to +85°C)

Connection Diagram



Order Number DS90LV017ATM See NS Package Number M08A

Functional Diagram



TRI-STATE® is a registered trademark of National Semiconductor Corporation.

Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

Supply Voltage (V _{CC})	-0.3V to +4V
Input Voltage (DI)	-0.3V to +3.6V
Output Voltage (DO±)	-0.3V to +3.9V
Maximum Package Power Dissi	pation @ +25°C
M Package	1190 mW
Derate M Package	9.5 mW/°C above +25°C
Storage Temperature Range	−65°C to +150°C
Lead Temperature Range Solde	ering
(4 sec.)	+260°C

ESD Ratings

	•	
(⊢	IBM 1.5 kΩ, 100 pF)	≥ 8kV
(E	EIAJ 0 Ω, 200 pF)	$\geq 1000V$
(C	CDM)	$\geq 1000V$
(18	EC direct 330 Ω, 150 pF)	$\geq 4kV$

Recommended Operating Conditions

	Min	Тур	Max	Units
Supply Voltage (V_{CC})	3.0	3.3	3.6	V
Temperature (T _A)	-40	25	+85	°C

Electrical Characteristics

Over Supply Voltage and Operating Temperature ranges, unless otherwise specified. (Notes 2, 3, 7)

Symbol	Parameter	Conditions		Pin	Min	Тур	Max	Units
DIFFERENTIAL DRIVER CHARACTERISTICS								
V _{OD}	Output Differential Voltage	$R_L = 100\Omega$		DO+,	250	355	450	mV
ΔV_{OD}	V _{OD} Magnitude Change	(Figure 1)		DO-		1	35	mV
V _{OH}	Output High Voltage					1.4	1.6	V
V _{OL}	Output Low Voltage				0.9	1.1		V
Vos	Offset Voltage				1.125	1.2	1.375	V
ΔV_{OS}	Offset Magnitude Change				0	3	25	mV
I _{OXD}	Power-off Leakage	V _{OUT} = V _{CC} or	$V_{OUT} = V_{CC}$ or GND, $V_{CC} = 0V$			±1	±10	μA
IOSD	Output Short Circuit Current			1		-5.7	-8	mA
V _{IH}	Input High Voltage			DI	2.0		V _{cc}	V
VIL	Input Low Voltage]	GND		0.8	V
I _{IH}	Input High Current	V _{IN} = 3.3V or 2	V _{IN} = 3.3V or 2.4V			±2	±10	μA
I	Input Low Current	$V_{IN} = GND \text{ or } 0.5V$		1		±1	±10	μA
V _{CL}	Input Clamp Voltage	$I_{CL} = -18 \text{ mA}$]	-1.5	-0.6		V
I _{cc}	Power Supply Current	No Load	$V_{IN} = V_{CC}$ or GND	V _{CC}		5	8	mA
		$R_L = 100\Omega$]			7	10	mA

Switching Characteristics

Over Supply Voltage and Operating Temperature Ranges, unless otherwise specified. (Notes 3, 4, 5, 6)

Symbol	Parameter	Conditions	Min	Тур	Max	Units
DIFFEREN	DIFFERENTIAL DRIVER CHARACTERISTICS					
t _{PHLD}	Differential Propagation Delay High to Low	$R_{L} = 100\Omega, C_{L} = 15 \text{ pF}$	0.3	0.8	1.5	ns
t _{PLHD}	Differential Propagation Delay Low to High	(Figure 2 and Figure 3)	0.3	1.1	1.5	ns
t _{SKD1}	Differential Pulse Skew It _{PHLD} - t _{PLHD} I (Note 8)		0	0.3	0.7	ns
t _{SKD3}	Differential Part to Part Skew (Note 9)		0		1.0	ns
t _{SKD4}	Differential Part to Part Skew (Note 10)		0		1.2	ns
t _{TLH}	Transition Low to High Time		0.2	0.5	1.0	ns
t _{THL}	Transition High to Low Time]	0.2	0.5	1.0	ns
f _{MAX}	Maximum Operating Frequency (Note 11)]		350		MHz

Note 1: "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. They are not meant to imply that the devices should be operated at these limits. The table of "Electrical Characteristics" specifies conditions of device operation.

Note 2: Current into device pins is defined as positive. Current out of device pins is defined as negative. All voltages are referenced to ground except V_{OD}.

Note 3: All typicals are given for: $V_{CC} = +3.3V$ and $T_A = +25^{\circ}C$.

Note 4: These parameters are guaranteed by design. The limits are based on statistical analysis of the device performance over PVT (process, voltage, temperature) ranges.

Note 5: C_L includes probe and fixture capacitance.

Switching Characteristics (Continued)

Note 6: Generator waveform for all tests unless otherwise specified: f = 1 MHz, $Z_O = 50\Omega$, $t_f \le 1 \text{ ns}$, $t_f \le 1 \text{ ns}$ (10%-90%).

Note 7: The DS90LV017A is a current mode device and only function with datasheet specification when a resistive load is applied to the drivers outputs.

Note 8: t_{SKD1}, It_{PHLD} - t_{PLHD}|, is the magnitude difference in differential propagation delay time between the positive going edge and the negative going edge of the same channel.

Note 9: t_{SKD3}, Differential Part to Part Skew, is defined as the difference between the minimum and maximum specified differential propagation delays. This specification applies to devices at the same V_{CC} and within 5°C of each other within the operating temperature range.

Note 10: t_{SKD4}, part to part skew, is the differential channel to channel skew of any event between devices. This specification applies to devices over recommended operating temperature and voltage ranges, and across process distribution. t_{SKD4} is defined as IMax – MinI differential propagation delay.

Note 11: f_{MAX} generator input conditions: $t_r = t_f < 1$ ns (0% to 100%), 50% duty cycle, 0V to 3V. Output criteria: duty cycle = 45%/55%, $V_{OD} > 250$ mV.

Parameter Measurement Information



FIGURE 1. Differential Driver DC Test Circuit







FIGURE 3. Differential Driver Propagation Delay and Transition Time Waveforms

Application Information

Pin #	Name Description		
2	2 DI1 TTL/CMOS driver input pins		
7	7 DO1+ Non-inverting driver output pin		
8	DO1-	Inverting driver output pin	
4	GND Ground pin		
1	V _{cc}	Positive power supply pin, $+3.3V \pm 0.3V$	
3, 5, 6	NC	No connect	

TABLE 1. Device Pin Descriptions

Typical Performance Curves



Output Low Voltage vs Power Supply Voltage



Differential Output Voltage vs Power Supply Voltage



Output Short Circuit Current vs Power Supply Voltage Output Short Circuit Current (mA) -5.80 -5.75 -5.70 -5.65 -5.60 $T_A = 25°C$ = V_{CC} or GND -5.55 VIN $V_{OUT} = 0V$ os

3.3

 V_{CC} - Power Supply Voltage (V)

-5.50

3.0

3.6

10010109







DS90LV017A

