

QMA Male Right Angle Connector Crimp/Non-Solder Contact Attachment for LMR-240, LMR-240-DB, LMR-240-FR, and 240-Series Cable



## EZ-240-QM-RA-X-LC



# Times Microwave Systems Connector Specification Configuration

- QMA Male Connector
- 50 Ohms
- · Right Angle Body Geometry

- LMR-240, LMR-240-DB, LMR-240-FR, 240-Series Interface Type
- Crimp/Non-Solder Contact Attachment

#### **Features**

- Designed to industry standard interface dimensions
- · Quality body materials and plating

### **Applications**

- RF Boxes and components
- · RF Test systems

- Crimp/Non-Solder Contact attachment
- · Operates to 6 GHz
- General Purpose RF Interconnect
- · Laboratory applications

## Description

L-com's QMA Male connector for LMR-240, LMR-240-DB, LMR-240-FR and 240-Series coax uses a Crimp/Non-Solder Contact attachment method. This QMA connector is one of the many RF coaxial connectors in L-com's product line up and like all our products, they will ship the same day. Our QMA Male connector operates up to a maximum frequency of 6 GHz.

The specifications and a basic dimensional drawing for EZ-240-QM-RA-X-LC Male QMA connector can be found in this datasheet PDF. L-com's portfolio of RF and microwave connectors allows users to choose from a large number of options when building assemblies to fit their RF interconnect needs. RF cables can be created to fulfill many interconnect applications ranging from In the Box hookup, test equipment connectivity or as part of a system installation. In addition to an offering of RF connectors and coaxial cable L-com offers both standard and custom cable assemblies to fit a customer's specific needs.

## **Electrical Specifications**

	6	GHz
	1.3:1	
	0.25	dB
Dielectric Withstanding Voltage (DC)		
		MOhms
		1.3:1

# **Mechanical Specifications**

Weight	0.027lbs	[12.25g]
Mating Cycles	100Cycles	

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: QMA Male Right Angle Connector Crimp/Non-Solder Contact Attachment for LMR-240, LMR-240-DB, LMR-240-FR, and 240-Series Cable EZ-240-QM-



QMA Male Right Angle Connector Crimp/Non-Solder Contact Attachment for LMR-240, LMR-240-DB, LMR-240-FR, and 240-Series Cable



# EZ-240-QM-RA-X-LC



## **Material Specifications**

Description	Material	Plating
Contact	Beryllium Copper	Gold
		50 μ inches
Insulation	PTFE	
Outer Conductor	Copper	Tri-Metal
		80 μ inches
Body	Brass	Tri-Metal
		80 μ inches
Coupling Nut	Brass	Tri-Metal
		80 μ inches

## **Environmental Specifications**

**Temperature** 

Operating Range 40°C to 125°C

Shock MIL-STD 202G, Meth. 213, Cond.I Vibration MIL-STD 202G, Meth. 204, Cond.D Thermal Shock MIL-STD 202G, Meth. 107, Cond.B

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

QMA Male Right Angle Connector Crimp/Non-Solder Contact Attachment for LMR-240, LMR-240-DB, LMR-240-FR, and 240-Series Cable from L-com has same day shipment for domestic and International orders. Our portfolio includes coaxial cable assemblies, connectors, adapters and custom products as well as lightning and surge protectors, NEMA rated enclosures, and an RF product line which includes antennas, amplifiers, passive, and active components. Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: QMA Male Right Angle Connector Crimp/Non-Solder Contact Attachment for LMR-240, LMR-240-DB, LMR-240-FR, and 240-Series Cable EZ-240-QM-RA-X-LC

URL: https://www.l-com.com/qma-male-right-angle-connector-crimp-non-solder-contact-attachment-lmr-240-lmr-240-db-lmr-240-fr-240-series-cable-ez-240-qm-ra-x-lc-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.ontained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. L-com reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. L-com does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and L-com does not assume liability arising out of the use of any part or document.

# **L-com CAD Drawing**

