



## Description:

This P-Channel MOSFET uses advanced trench technology and design to provide excellent  $R_{DS(on)}$  with low gate charge. It can be used in a wide variety of applications.

#### Features:

- 1)  $V_{DS}$ =-30V, $I_D$ =-4.1A, $R_{DS(ON)}$ <55m  $\Omega$  @ $V_{GS}$ =-10V
- 2) Low gate charge.
- 3) Green device available.
- 4) Advanced high cell denity trench technology for ultra R<sub>DS(ON)</sub>.
- 5) Excellent package for good heat dissipation.





# Package Marking and Ordering Information:

Part NO.	Marking	Package	Packing
DO3407B	3407B	3407B SOT-23 300	

## Absolute Maximum Ratings: (T<sub>A</sub>=25℃ unless otherwise noted)

Symbol	Parameter	Ratings	Units
V <sub>DS</sub>	Drain-Source Voltage	-30	V
V <sub>GS</sub>	Gate-Source Voltage	±20	V
	Continuous Drain Current-T <sub>A</sub> =25°C	-4.1	
I <sub>D</sub>	Continuous Drain Current-T <sub>A</sub> =70℃	-2.7	A
I <sub>DM</sub>	Pulsed Drain Current <sup>1</sup>	-16.4	
P <sub>D</sub>	Power Dissipation	1.3	W
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range	-55 to +150	$^{\circ}\!\mathrm{C}$

## Thermal Characteristics:

Symbol	Parameter	Max	Units
R <sub>OJA</sub>	Thermal Resistance, Junction to Ambient <sup>2</sup>	96	°C/W



# Electrical Characteristics: (T<sub>A</sub>=25℃ unless otherwise noted)

Symbol	Parameter	Conditions	Min	Тур	Max	Units
Off Characteristics	Off Characteristics					
BV <sub>DSS</sub>	Drain-Sourtce Breakdown Voltage	V <sub>GS</sub> =0V,I <sub>D</sub> =-250 μ A	-30			V
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	V <sub>GS</sub> =0V, V <sub>DS</sub> =-30V			-1	μ Α
I <sub>GSS</sub>	Gate-Source Leakage Current	$V_{GS}=\pm 20V$ , $V_{DS}=0V$			±100	nA
On Characteristics						
V <sub>GS(th)</sub>	Gate -Source Threshold Voltage	V <sub>GS</sub> =V <sub>DS</sub> , I <sub>D</sub> =-250 μ A	-1	-1.5	-2.5	V
		V <sub>GS</sub> =-10V,I <sub>D</sub> =-4A		37	55	m Ω
R <sub>DS(ON)</sub>	Drain-Source On Resistance <sup>3</sup>	V <sub>GS</sub> =-4.5V,I <sub>D</sub> =-3A		50	70	
Dynamic Characteristics						
C <sub>iss</sub>	Input Capacitance			575		
C <sub>oss</sub>	Output Capacitance	V <sub>DS</sub> =-15V, V <sub>GS</sub> =0V, f=1MHz		65		pF
C <sub>rss</sub>	Reverse Transfer Capacitance			58		
Switching Characteris	Switching Characteristics					
t <sub>d(on)</sub>	Turn-On Delay Time			3		ns
t <sub>r</sub>	Rise Time	V <sub>DD</sub> =-15V,V <sub>GS</sub> =-10V		2		ns
t <sub>d(off)</sub>	Turn-Off Delay Time	$R_{GEN}=2.5 \Omega$ , $I_D=-1A$		26		ns
t <sub>f</sub>	Fall Time			14		ns
Qg	Total Gate Charge			12.5		nC
$\mathbf{Q}_{gs}$	Gate-Source Charge	V <sub>GS</sub> =-10V, V <sub>DS</sub> =-15V,		2.2		nC
$\mathbf{Q}_{gd}$	Gate-Drain "Miller" Charge	I <sub>D</sub> =-4.1A		2.1		nC
Drain-Source Diode Characteristics						
V <sub>SD</sub>	Source-Drain Diode Forward Voltage	V <sub>GS</sub> =0V,I <sub>S</sub> =-4.1A		-0.8	-1.2	V
Is	Continuous Drain Curren				-4.8	А
I <sub>SM</sub>	Pulsed Drain Current	$V_D=V_G=0V$			-16.4	А



#### **Notes:**

- 1. Repetitive Rating: Pulse Width Limited by Maximum Junction Temperature.
- 2.  $R_{\theta JA}$  is measured with the device mounted on a 1inch<sup>2</sup> pad of 2oz copper FR4 PCB
- 3. Pulse Test: Pulse Width≤300µs, Duty Cycle≤0.5%.

## Typical Characteristics: (Tc=25°C unless otherwise noted)




Figure 1: Output Characteristics




Figure 3: On-resistance vs. Drain Current





Figure 5: Gate Charge Characteristics



**Figure 2: Typical Transfer Characteristics** 




Figure 4: Body Diode Characteristics




Figure 6: Capacitance Characteristics






Figure 7: Normalized Breakdown voltage vs.
Junction Temperature




Figure 9: Maximum Safe Operating Area




Figure 11: Normalized Maximum Transient Thermal Impedance




Figure 8: Normalized on Resistance vs.

Junction Temperature




Figure 10: Maximum Continuous Drian Current vs. Ambient Temperature





Figure 12: Peak Current Capacity




### **SOT-23-3 Package Outline Data**





## Marking Information:



## Previous Version

Version	Date	Subjects (major changes since last revision)	
2.0	2024-06-08	Release of final version	

#### Attention:

- Information furnished in this document is believed to be accurate and reliable. However, Shenzhen Doingter Semiconductor Co.,Ltd. assumes noresponsibility for the consequences of use without consideration for such information nor use beyond it.
- Information mentioned in this document is subject to change without notice, apart from that when an agreement is signed, Shenzhen Doingter complies with the agreement.

  Products and information provided in this document have no infringement of patents.
- Shenzhen Doingter assumes noresponsibility for any infringement of other rights of third parties which may result from the use of such products and information. This document supersedes and replaces all information previously supplied.

  Is a registered trademark of Shenzhen Doingter Semiconductor Co., Ltd. Copyright © 2013 Shenzhen DoingterSemiconductor Co., Ltd. Printed All rights reserved.