

**CHARACTERISTICS MATERIALS** 

**HOUSING: ABS+PC** HOUSING COLOR: GREY COLLET NUT: ABS+PC **CONTACTS: COPPER ALLOY** 

CONTACT PLATING: 7µ" GOLD PLATED OVER 196µ" NICKEL MIN. INSULATOR: PPS (HIGH TEMPERATURE)


**MECHANICAL** 

**DURABILITY: 2000 CYCLES** 

OPERATING TEMP. RANGE: -20° C ~ +120° C PROCESS TEMPERATURE: 260°C FOR 5 SECONDS

MAX. TORQUE VALUE: 0.5 Nm [4.4 IN/LBS]

IP RATING: 50



#### CHART B

COLLET SIZE	WIRE DIAMETER			
42	2.20 [0.087] ~ 4.00 [0.157]			
52	4.00 [0.157] ~ 5.00 [0.197]			
62	5.00 [0.197] ~ 6.00 [0.236]			



14 POSITION 26 AWG MAX. 2 AMP MAX. PIN  $\emptyset = 0.50 [0.020]$ 

CONTACT RESISTANCE =  $10 \text{ m}\Omega$ TEST VOLTAGE = 600V WORKING VOLTAGE = 200V

### CHART A







2 POSITION 22 AWG MAX. 10 AMP MAX. PIN  $\emptyset = 1.30 [0.051]$ 

CONTACT RESISTANCE =  $5 \text{ m}\Omega$ TEST VOLTAGE = 1200V WORKING VOLTAGE = 400V



3 POSITION 22 AWG MAX. 10 AMP MAX. PIN Ø = 1.30 [0.051]

CONTACT RESISTANCE =  $5 \text{ m}\Omega$ TEST VOLTAGE = 1200V WORKING VOLTAGE = 400V



4 POSITION 22 AWG MAX. 8 AMP MAX. PIN Ø = 0.90 [0.035]

CONTACT RESISTANCE =  $6 \text{ m}\Omega$ TEST VOLTAGE = 1200V WORKING VOLTAGE = 400V



5 POSITION 22 AWG MAX. 7 AMP MAX. PIN Ø = 0.90 [0.035]

CONTACT RESISTANCE =  $6 \text{ m}\Omega$ TEST VOLTAGE = 1050V WORKING VOLTAGE = 350V



6 POSITION 24 AWG MAX. 6 AMP MAX. PIN Ø = 0.70 [0.028]

CONTACT RESISTANCE =  $7.5 \text{ m}\Omega$ TEST VOLTAGE = 1050V WORKING VOLTAGE = 350V



7 POSITION 24 AWG MAX. 5 AMP MAX. PIN Ø = 0.70 [0.028]

CONTACT RESISTANCE =  $7.5 \text{ m}\Omega$ TEST VOLTAGE = 1050V WORKING VOLTAGE = 350V



8 POSITION 24 AWG MAX. 5 AMP MAX. PIN Ø = 0.70 [0.028]

CONTACT RESISTANCE =  $7.5 \text{ m}\Omega$ TEST VOLTAGE = 1050V WORKING VOLTAGE = 350V



9 POSITION 26 AWG MAX. 3 AMP MAX. PIN Ø = 0.50 [0.020]

CONTACT RESISTANCE =  $10 \text{ m}\Omega$ TEST VOLTAGE = 850V WORKING VOLTAGE = 280V



10 POSITION 26 AWG MAX. 3 AMP MAX. PIN  $\emptyset = 0.50 [0.020]$ 

CONTACT RESISTANCE =  $10 \text{ m}\Omega$ TEST VOLTAGE = 850V WORKING VOLTAGE = 280V

#### **Rohs Compliant**



THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF NorComp AND SHALL NOT BE REPRODUCED, COPIED OR USED AS THE BASIS FOR THE MANUFACTURE OR SALE OF APPARATUS WITHOUT WRITTEN PERMISSION.



DRAWN:	DATE:	SCALE:	SHEET	OF		REV:
M. SIGMON	08-01-16	N.T.S.	1		1	2
			DWG NO.  8P1PYYY17NYLYY1			

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## NorComp:

```
8P1P00717NRL621 8P1P01417NVL521 8P1P00517NVL421 8P1P00517NRL521 8P1P00717NJL521
8P1P00317NJL621 8P1P00217NNL521 8P1P00217NJL621 8P1P00317NNL521 8P1P00617NAL421
8P1P00417NNL521 8P1P00417NAL621 8P1P00917NVL421 8P1P01017NGL421 8P1P01017NJL621
8P1P00717NAL621 8P1P00817NAL421 8P1P00817NVL421 8P1P00817NGL521 8P1P00917NJL421
8P1P00517NVL621 8P1P00417NGL421 8P1P00917NRL521 8P1P00317NAL521 8P1P00617NGL621
8P1P01017NAL621 8P1P01017NAL421 8P1P00817NJL621 8P1P00617NNL621 8P1P00417NRL621
8P1P00917NGL521 8P1P01017NRL621 8P1P00817NJL521 8P1P01017NGL621 8P1P00517NJL621
8P1P01017NJL521 8P1P00917NGL621 8P1P00717NGL421 8P1P01417NGL521 8P1P00417NVL621
8P1P00917NJL621 8P1P00617NRL421 8P1P00617NAL521 8P1P00717NRL421 8P1P00217NGL521
8P1P00417NVL421 8P1P00517NVL521 8P1P00817NRL521 8P1P01017NNL421 8P1P00317NGL521
8P1P00317NVL521 8P1P01417NAL521 8P1P00317NAL421 8P1P01017NAL521 8P1P00417NGL521
8P1P00517NNL521 8P1P00717NGL621 8P1P01017NNL621 8P1P00417NJL521 8P1P00617NNL521
8P1P00217NAL521 8P1P00517NAL421 8P1P01417NGL621 8P1P00317NJL421 8P1P01417NRL421
8P1P01417NJL621 8P1P00417NNL421 8P1P00717NAL421 8P1P00617NGL521 8P1P00517NJL521
8P1P00617NVL421 8P1P01417NRL521 8P1P00517NGL521 8P1P00717NVL621 8P1P00617NAL621
8P1P00617NNL421 8P1P00617NJL621 8P1P00417NAL521 8P1P00617NJL521 8P1P00917NAL521
8P1P00317NGL421 8P1P00917NNL521 8P1P00217NRL521 8P1P00217NJL521 8P1P01417NNL621
8P1P00417NAL421 8P1P01417NAL621 8P1P00917NAL621 8P1P00717NVL521 8P1P00217NGL421
8P1P00817NVL621 8P1P00817NNL621 8P1P01417NJL421 8P1P00417NJL621 8P1P00617NRL621
8P1P01017NVL621 8P1P01017NRL421 8P1P00217NRL421 8P1P00217NAL421 8P1P01417NVL621
```