

www.lemo.com

# CRC.M26.GLL.C72VZ

# **SUMMARY**

#### # Wires

Low voltage 26



Image is for illustrative purpose only

Series 2P

**Termination type** Female solder

IP rating 50

AWG wire size 34.00 - 28.00 Cable Ø 5.30 - 7.20 mm

**Status** active

#### **Download**

Request a quote

Catalog

# **TECHNICAL DETAILS**

#### **Mechanics**

Shell Style/Model CR\*: Free receptacle with cable collet and nut for fitting a bend relief

Keying 3 keys (alpha=0, gamma=100; Plug: male contacts; Receptacle: female contacts)

Housing Material PSU (Polysulfone), gray

**Weight** 10.29 g

#### **Performance**

Configuration 2P.M26: 26 Low V.

Insulator L: PEEK for solder contacts

Rated Current 2 Amps

### **Specifications**

Contact Type: Solder

Contact Dia.: 0.5 mm (0.019in) Bucket Dia.: 0.5 mm (0.019in)

Test voltage (kV rms) Contact-contact: 1

Air clearance min.: 0.55 mm Creepage distance min.: 0.55 mm

## Others

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.


Endurance (Shell): >1000 mating cycles Temp (min / max): -50°C / +150°C


F ret (min): 150 N F ret (max): 250 N


R leak (He) (max): 0.0000001 mbar\*l/s (if vacuum-tested)

Steam sterilization: 20 times

# **DRAWINGS**







## **Dimensions**

	Α	L
mm.	18	56
in.	0,71	2,20

# **RECOMMENDED BY LEMO**

### **Tools**

### **Cables**

CMN.26.T28.070PGZE	Grey	
CMN.26.T28.070PNZE		

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.



LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.