

Note: This datasheet may be out of date. Please download the latest datasheet of PTGL9SAS1R2K2B51B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=PTGL9SAS1R2K2B51B0

PTGL9SAS1R2K2B51B0











Appearance & Shape







Applications

Automotive Usage	Infotainment
Limited Usage	Automotive Grade



Packaging Information

Packaging		Standard Packing
		Quantity
В0	Bulk(Bag)	500



Features

- 1. Useful protective threshold current range with a wide temperature range.
- 2. Small fluctuation in the circuit due to resistance tolerance +/-
- 3. Quick operating time due to small size compared with conventional products.
- 4. Best suited to meet the requirements of power supply and motor protector. Error-free operation is assured by rush current.
- 5. Circuit is protected until current is turned off.
- 6. Restores the original low resistance value automatically once the overload is removed.
- 7. Non-contact design leads to long life and no noise. Durable and strong against mechanical vibration and shock because it is a solid element.
- 8. Lead (Pb) is not contained in the terminations.

1 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of PTGL9SAS1R2K2B51B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=PTGL9SAS1R2K2B51B0

PTGL9SAS1R2K2B51B0



Specifications

Max. Voltage	30V
Hold Current(25°C)	704mA
Measure Condition of Hold Current	(at +25°C)
Hold Current (2)	422mA
Measure Condition of Hold Current (2)	(at +85°C)
Hold Current (3)	296mA
Measure Condition of Hold Current (3)	(at +105°C)
Trip Current(25°C)	936mA
Measure Condition of Trip Current	(at +25°C)
Trip Current(2)	1193mA
Measure Condition of Trip Current(2)	(at -40°C)
Max. Current	6A
Resistance (25°C)	1.2Ω
Resistance Value Tolerance (at 25°C)	±10%
Curie Point(typ.)	130℃
Power Consumption(typ)	2W
Operating Temperature Range	-40°C to 125°C
D: Outer Dimension	9.3mm
Thickness	3.5mm
H: Height	14.3mm
F: Lead Space	5mm
d: Lead Diameter	0.6mm
Shape	Lead

Mass	0.44g
MSL	N

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Note: This datasheet may be out of date.


Please download the latest datasheet of PTGL9SAS1R2K2B51B0 from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en-us/products/productdetail?partno=PTGL9SAS1R2K2B51B0

PTGL9SAS1R2K2B51B0




Product Data





Resistance-Temperature Charac.



Protective Threshold Current Range

Operating Time (Typical Curve)

3 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

