



www.lemo.com

SUMMARY

Wires

Fiber optic 1



Image is for illustrative purpose only

Series 2B

Termination type Hybrid contacts

IP rating 50

AWG wire size 26.00 - 22.00 Cable Ø 0.00 - 0.00 mm

Status active

Matching parts FGG.2B.96C.CLCD62Z

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model EC*: Fixed receptacle with two nuts (back panel mounting)

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Weight 16.39 g

Performance

Configuration 2B.96C: 1 FO Type F1, 4 LV

Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 6 Amps

Specifications

Contact Type: Crimp

Fiber Optic Contact: Type F1 (must be ordered separately)

Vtest (contact-shell): 1250 V (AC), 1770 V (DC) Vtest (contact-contact): 850 V (AC), 1200 V (DC)

Others

Endurance (Shell): 5000


LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Temp (min / max): -40°C / +80°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS





Dimensions

	A	В	E	L	М	N	S 1	\$3	e
mm.	20	19.2	6.5	26.7	3.5	24.6	13.5	17	M15x1.0
in.	0,79	0,76	0,26	1,05	0,14	0,97	0,53	0,67	

RECOMMENDED BY LEMO

Tools

Crimp settings: AWG/Selector = 22-24-26/6-5-5

Positionner: DCE.91.072.BVM
Extractor: DCC.91.070.5LA
Extractor 2: DCF.91.070.2LT

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Spanner 2: <u>DCH.91.201.PA</u>

Replacement contact: EGG.2B.655.ZZM

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.