

EP Cores (6595130121)



Part Number: 6595130121

95 EP CORE SET

EP designs reduce the effect of residual air gap upon the effective permeability of the core, hence they minimize coil volume for a given inductance. EP cores also provide a high degree of isolation from adjacent components and are advantageously used in low power devices, matching and broadband transformers.

 \Box EP cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicates is per pair or set.

Weight: 2.35 (g)

11 01511		0			
Dim	mm	mm tol	nominal inch	inch misc.	
A	12.5	± 0.30	0.492	_	c B
В	6.5	± 0.30	0.256	_	
C	8.8	± 0.20	0.346		
D	4.7	± 0.20	0.185	_	
Е	10	± 0.30	0.394	_	- K - -D-
F	4.4	± 0.20	0.173	_	
K	2.5	min	0.098		

Chart Legend

 $\Sigma I/A$: Core Constant, I_e : Effective Path Length, A_e : Effective Cross-Sectional Area, V_e :

Effective Core Volume
A_L: Inductance Factor

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties		
$A_L(nH)$	1800 ±25%	
Ae(cm ²)	0.197	
$\Sigma l/A(cm^{-1})$	11.8	
l _e (cm)	2.32	
$V_e(cm^3)$	0.457	
$A_{min}(cm^2)$	0.148	

A_r value is measured at 1 kHz, B < 10 gauss

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288

888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • • www.fair- rite.com