

FHG.2B.810.CLAD72Z

SUMMARY

Wires

Low voltage 10 Coax 1

Series 2B

Termination type Male solder mixed / multi coax

IP rating 50

AWG wire size 30.00 - 22.00 Cable Ø 6.30 - 7.20 mm

Status active

Matching parts EGG.2B.810.CLL2



Image is for illustrative purpose only

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model FH*: Elbow plug, cable collet and nut for fitting a bend relief

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Variant Z: Nut for fitting a bend relief

Weight 44.23 g

Performance

Configuration 2B.810: 1 Coax (50 Ohm), 10 Low V.

Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 7 Amps

Specifications

Contact Type: Coaxial 50 Ohm (Crimp) Type C

Contact Dia.: 0.7 mm (0.03in)

R (max): 5.8 mOhm

Test voltage (kV rms): 0.95 Test voltage (kV dc): 1.35

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Others


Endurance (Shell): 5000


Temp (min / max): -55°C / +250°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS







Dimensions

	A	D	н	L	М	S 1	S2	S 3
mm.	16.5	9	34.3	41.5	29.5	14	12	14
in.	0,65	0,35	1,35	1,63	1,16	0,55	0,47	0,55

RECOMMENDED BY LEMO

Tools

Extractor: DCC.91.384.5LA
Die Tool: DPE.99.103.1K

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Spanner wrench: DCD.2B.025.PA120