

# FHB.2B.326.CLAD92

# **SUMMARY**

### # Wires

Low voltage 26

Image is for illustrative purpose only

Series 2B

Termination type Male solder

IP rating 50

AWG wire size 34.00 - 28.00

Cable Ø 8.30 - 9.20 mm

**Status** active

Matching parts EGB.2B.326.CLL

#### **Download**

Request a quote

Eplan Catalog

# **TECHNICAL DETAILS**

## **Mechanics**

Shell Style/Model FH\*: Elbow plug, cable collet

**Keying** 2 keys (alpha=45, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Weight 40.17 g

#### **Performance**

Configuration 2B.326 : 26 Low Voltage Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 2 Amps

# **Specifications**

Contact Type: Solder

Contact Dia.: 0.5 mm (0.02in) Bucket Dia.: 0.45 mm (0.018in)

Max. Solid Conductor: 0.09 mm<sup>2</sup> (AWG 28) Max. Stranded Conductor: 0.09 mm<sup>2</sup> (AWG 28)

R (max): 8.7 mOhm

Vtest (contact-shell): 1300 V (AC), 1840 V (DC) Vtest (contact-contact): 950 V (AC), 1340 V (DC)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

### **Others**

Endurance (Shell): 5000


Temp (min / max): -55°C / +250°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [ 6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

# **DRAWINGS**







## **Dimensions**

	А	D	н	L	М	<b>S</b> 1	S2	S3
mm.	16.5	9	34	41.5	29.5	14	12	13
in.	0,65	0,35	1,34	1,63	1,16	0,55	0,47	0,51

# **RECOMMENDED BY LEMO**

### **Tools**

Spanner wrench: DCD.2B.025.PA120

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

