

FHG.1K.304.CYCC60Z

SUMMARY

Wires

Low voltage 4

Image is for illustrative purpose only

Series 1K

Termination type Male crimp

IP rating 68

AWG wire size 24.00 - 20.00 Cable Ø 5.60 - 6.00 mm

Status active

Matching parts EGG.1K.304.CYM

Download

Request a quote

Catalog

TECHNICAL DETAILS

Mechanics

Shell Style/Model FH*: Elbow plug, cable collet and nut for fitting a bend relief

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

Variant Z: Nut for fitting a bend relief

Performance

Configuration 1K.304: 4 Low Voltage

Insulator Y: PEEK for crimp contacts

Rated Current 10 Amps

Specifications

Contact Type: Crimp Contact Retention: 30 N Contact Dia.: 0.9 mm (0.035in)

Bucket Dia.: 1.1 mm (0.043in) Min. Conductor: 0.25 mm^2 (AW)

Min. Conductor: 0.25 mm² (AWG 24) Max. Conductor: 0.5 mm² (AWG 20)

R (max): 4.8 mOhm

Vtest (contact-shell): 1800 V (AC), 2550 V (DC)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Vtest (contact-contact): 1700 V (AC), 2400 V (DC)

Others


Endurance (Shell): 5000 mating cycles Temp (min / max): -55°C / +200°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [6 ms] Climatical Category: 50/175/21 Shielding (min): 95 dB (10 MHz) Shielding (min): 80 dB (1 GHz) Salt Spray Corrosion: >1000 hr

DRAWINGS







Dimensions

	А	D	L	М	S 1	S2	S 3
mm.	14	8.8	43	29	12	9	10
in.	0,55	0,35	1,69	1,14	0,47	0,35	0,39

RECOMMENDED BY LEMO

Tools

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Crimp Tool: <u>DPC.91.701.V</u>

Crimp settings: AWG/Selector = 20-22-24/6-5-5

Positionner: DCE.91.091.BVC
Extractor: DCF.91.090.2LT
Replacement contact: FGG.1B.560.ZZC
Spanner wrench: DCD.1E.008.PA090

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.