

# FHG.2K.308.CLAK90

## **SUMMARY**

### # Wires

Low voltage 8

Image is for illustrative purpose only

Series 2K

Termination type Male solder

IP rating 68

AWG wire size 30.00 - 22.00

Cable Ø 8.60 - 9.00 mm

Status active

Matching parts EGG.2K.308.CLL

### Download

Request a quote

Catalog

## **TECHNICAL DETAILS**

#### **Mechanics**

**Shell Style/Model** FH\*: Elbow plug, cable collet

Keying 1 key (alpha=0, plug: male contacts, receptacle: female contacts)

Housing Material

Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290]

brass latch sleeve and mid pieces

**Weight** 71.63 g

### **Performance**

Configuration 2K.308: 8 Low Voltage Insulator L: PEEK (UL 94 / V-0/1.5)

Rated Current 10 Amps

## **Specifications**

Contact Type: Solder

Contact Dia.: 0.9 mm (0.035in) Bucket Dia.: 0.8 mm (0.031in)

Max. Solid Conductor: 0.34 mm<sup>2</sup> (AWG 22) Max. Stranded Conductor: 0.34 mm<sup>2</sup> (AWG 22)

R (max): 4.8 mOhm

Vtest (contact-shell): 1250 V (AC), 1770 V (DC) Vtest (contact-contact): 1500 V (AC), 2150 V (DC)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.


### **Others**


Endurance (Shell): 5000 mating cycles Temp (min / max): -55°C / +200°C

Humidity (max): <=95% [at 60 deg C /140 F]

Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [ 6 ms] Climatical Category: 50/175/21 Shielding (min): 95 dB (10 MHz) Shielding (min): 80 dB (1 GHz) Salt Spray Corrosion: >1000 hr

## **DRAWINGS**







### **Dimensions**

	А	D	н	L	М	<b>S</b> 1	S2	<b>S</b> 3
mm.	17.5	10.5	40	51	35	15	12	13
in.	0,69	0,41	1,57	2,01	1,38	0,59	0,47	0,51

# **RECOMMENDED BY LEMO**

## Tools

Spanner wrench: DCD.2E.020.PA120

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

