

TRIAC BT136


FEATURES


This device of sensitive TRIAC product is a glass passivated device, has a low gate trigger current, high stability in gate trigger current to variation of operating temperature and high off state voltage.

APPLICATIONS

This device is suitable for low power AC switching application, phase control application such as fan speed and temperature modulation control, lighting control and static switching relay.

SYMBOL:





Tel: +86-755-83677999

ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	VALUE			UNIT	
Repetitive Peak Off-State Voltages	V _{DRM} , V _{RRM}	BT136-600D/E 600		V		
		BT136	-800D/E	800	V	
RMS on-State Current	I _{T(RMS)}	4			Α	
Non-Repetitive Peak On-State Current	I _{TSM}	35			Α	
I ² t for fusing	l²t	6.1			A ² s	
Repetitive rate of rise of on-state current after triggering	dIT/dt	I	50			
		II	50		A/uS	
		III	50			
		IV	10			
Peak gate current	I _{GM}	2			Α	
Peak Gate Power	P _{GM}	5			W	
Average Gate Power	$P_{G(AV)}$	0.5			W	
Operating junction temperature	TJ	-40~+125			$^{\circ}$	
Storage Temperature	T _{STG}	-40 ~ +150			${\mathbb C}$	



TRIAC BT136

ELECTRICAL CHARACTERISTICS (TJ=25°C)

DADAMETED	OVMDOL	TEST CONDITIONS		MIN	MAX		LINUTC
PARAMETER	SYMBOL	IESI CON	D		E	UNITS	
Peak Repetitive Forward or Reverse Blocking Current	I _{DRM} I _{RRM}	V_{AK} = Rated V_{DRM} or V_{RRM} ;			5		uA
Gate Trigger Current	Іст	V _D =12V, R _L =100Ω	I		5	10	mA
			II		5	10	
			III		5	10	
			IV		10	25	
Gate Trigger Voltage	V_{GT}	$V_D=12V$, $R_L=100\Omega$			1.5		V
Peak Forward On-State Voltage	V_{TM}	IT=5.5A			1.6		V
Latch Current	IL	lg=1.2lgт	1		15	15	- mA
			II		20	25	
			Ш		15	15	
			IV		15	15	
Holding Current	lн	I _T =0.1A			12	12	mA
Gate Non-Trigger Voltage	V_{GD}	V _D =V _{DRM}		0.2			V
Critical Rate of Rise of Off-State Voltage	dV/dt	V_D =67% V_{DRM} , R_{GK} =1 $k\Omega$		50			V/µs

Tel: +86-755-83677999