

产品承认书 SPECIFICATION FOR APPROVAL

| 客户名称: CUSTOMER | | | | | |
|-----------------------------|-------------------------|------------|--------------|----------------|--|
| 我司料号: OUR PART NO. | | | | | |
| 我司品名: OUR PART NAME | SMT | RS | | | |
| 送样日期: DATE SAMPLES | | | | | |
| | 制造确认 | MANUFACTI | URER APPR | OVE | |
| 拟制 DRA | WN | 审核 CHECKED | | 确认 APPROVED | |
| Hu Fangt | ing | RaoPing | LiZhengxiong | | |
| 客户名称 CUSTO 客户料号 CUSTO | OMER NAME: OMER P/N: | 的 CUSTOME | | Έ | |
| 规格型号 DESCR | | | | | |
| 检查結果: □ | 合格 □不合格 | - | 签名及 | 盖章 : | |
| INSPECT RESUI 说明 REMARK: | LT ACCEPT | REJECT | SIGNA | TURE AND STAMP | |

如对本承认书内容有异议请提出或标记发送至我司,本承认书在未收到异议回复时于本承认书提供一周后生效。

If you have any objection to the contents of this acknowledgment, please raise it or send the mark to us. The acknowledgment

will become effective one week after the acknowledgment is provided in the absence of any objection.

东莞市祥如电子有限公司

DONGGUAN XIANGRU ELECTRONICS CO., LTD

Tel: 0769-86346548 Fax: 0769-86346358

Email: dgxiangru@126.com



产品承认书 SPECIFICATION FOR APPROVAL

XRPAEE4-B1 Series

SMT CURRENT SENSETRANSFORMERS

Applications:


.Switching power supplies


.Feedback control.


.Overload sensing.


.Load drop/shut down detection.


Shape and Dimensions (Dimensions are in mm):











| Item | A MAX. | B MAX. | C MAY | E | F | G | Н | I | J |
|------------|--------|--------|----------|-----|-----|-----|-----|-----|-----|
| XRPAEE4-B1 | 5.40 | 7.20 | 3.00 | 0.4 | 1.2 | 2.6 | 1.2 | 1.1 | 1.2 |

Features:

.Very low DC resistance.

.Different turns ratios.

.Very small package

.RoHS compatible.

.500Vrms, one minute isolation(hipot)between windings

Product Identification:

XRPAEE4-B1-20TNL

1 2 3 4

(1) Type: Surface Mountable Type.

(2) Style:EE Core,4.6 is size.

(3) The primary turns: B1T

4) Secondary turns:20T

Sensed Current – primary rated for 20 Amps..



产品承认书 SPECIFICATION FOR APPROVAL

Characteristics:

.Primary current of 9 A causes less than 40°C temperature rise from 25°C ambient. Higher current causes a greater temperature rise

. Operating temperature :-40Cto125C. ohmmeter

.Storage temperature Component: -40°C to +165°C

.Inductance measured between secondary pins at

100KHz,0.1V Vrms,0 Adc

Test equipments:

Inductance measured at 0Adc on HP 4284A LCR Meter or equivalent

.DCR measured on Chroma 16502 micro-or equivalent.

Electrical specifications at 25℃.

Measuring Frequency:

XRPAEE4.4 @50KHZ TO 1MHZ

XRPAEE4-B1 Series

| David Na | Turns ratio | Secondary Inductance | DCR(Ω) | | Sensed | |
|-------------------|-------------|-------------------------|-----------------|---------|---------------------|--|
| Part No. | pri: sec: | @100KHZO.1V (mH)MIN | Sec Max Pri Ref | | Current(A) (Max) | |
| XRPAEE4-B1-20TNL | 1:20 | 0.053 | 0. 42 | 0. 0015 | 9 | |
| XRPAEE4-B1-50TNL | 1:50 | 0.333 | 2.76 | 0. 0015 | 9 | |
| XRPAEE4-B1-70TNL | 1:70 | 0.652 | 5.04 | 0. 0015 | 9 | |
| XRPAEE4-B1-100TNL | 1:100 | 1.330 | 10.68 | 0.0015 | 9 | |
| XRPAEE4-B1-150TNL | 1:150 | 2.993 | 22.30 | 0.0015 | 9 | |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |

XRPAEE4-B1 Temp Rise vs Current:

