# **Power Inductor**

DFP252012TF-R33M

## 1. Features

- 1. This specification applies Low Profile Power Inductors.
- 2. 100% Lead(Pb) & Halogen-Free and RoHS compliant.

## 2. Dimension





D E	
	D E

Series	A(mm)	B(mm)	C(mm)	D(mm)	E(mm)
DFP252012TF	2.5 -0.1/+0.2	2.0 -0.05/+0.35	1.2Max	0.85 ref.	0.80 ref.

Units: mm

## 3. Part Numbering

**DFP 252012 TF** - **R33 M**A B C D E

A: Series

B: Dimension

C: Lead Free Material
D: Inductance R33=0.33uH
E: Inductance Tolerance M=±20%

## 4. Specification

TAI-TECH Part Number	Inductance (uH)	Tolerance (%)	Test Frequency (Hz)	DCR (Ω) typ.	DCR (Ω) Max.	I sat (A) typ.	I sat (A) Max.	I rms (A) typ	I rms (A)Max.
DFP252012TF-R33M	0.33	±20%	0.1V/1M	0.027	0.032	5.70	4.60	4.50	4.00


Note:


Isat: Saturation Current (Isat) will cause L0 to drop approximately 30%.

Irms: Heat Rated Current (Irms) will cause the coil temperature rise approximately  $\,^{\vartriangle}\text{T}$  of 40  $^{\circlearrowright}$ 

### 5. Material List

No.	Description	Specification
a.	Core	Ferrite Core
b.	Wire	Enameled Copper Wire
С	Glue	Epoxy with magnetic powder
d	Terminal	Ag/Ni/Sn





Appearance of exposed wire tolerance limit:

- Width direction (dimension a): Acceptable when a ≤ w/2
   Nonconforming when a > w/2
- 2. Length direction (dimension b): Dimension b is not specified.
- 3. The total area of exposed wire occurring to each sides is not greater than 50% of coating resin area, and is acceptable.

## 6. Reliability and Test Condition

Item	Performance	Test Condition		
Operating temperature	-40~+125℃ (Including self - temperature rise)			
Storage temperature	110~+40°C,50~60%RH (Product with taping) 240~+125°C (on board)			
Electrical Performance Te	est			
		HP4284A,CH11025,CH3302,CH1320,CH1320S		
Inductance	Refer to standard electrical characteristics list.	LCR Meter.		
DCR		CH16502,Agilent33420A Micro-Ohm Meter.		
Seturation Comment (leat)	Annesidentals Al 2007	Saturation DC Current (Isat) will cause L0		
Saturation Current (Isat)	Approximately∆L30% .	to drop △L(%)(keep quickly).		
		Heat Rated Current (Irms) will cause the coil temperature rise		
Heat Rated Current (Irms)	Approximately △T40℃	$\triangle T(^{\circ}\!$		
Treat Nated Ourient (IIIIs)	Approximately 2140 C	1.Applied the allowed DC current(keep 1 min.).		
		2.Temperature measured by digital surface thermometer		
Reliability Test				
Life Test		Preconditioning: Run through IR reflow for 2 times.( IPC/JEDEC J-STD-020DClassification Reflow Profiles) Temperature: 125±2°C Applied current: rated current Duration: 1000±12hrs Measured at room temperature after placing for 24±2 hrs		
Load Humidity		Preconditioning: Run through IR reflow for 2 times.( IPC/JEDEC J-STD-020DClassification Reflow Profiles Humidity: 85±2% R.H, Temperature: 85℃±2℃ Duration: 1000hrs Min. with 100% rated current Measured at room temperature after placing for 24±2 hrs		
Moisture Resistance	Appearance: No damage. Inductance: within±10% of initial value Q: Shall not exceed the specification value. RDC: within ±15% of initial value and shall not exceed the specification value	Preconditioning: Run through IR reflow for 2 times.( IPC/JEDE J-STD-020DClassification Reflow Profiles 1. Baked at50°C for 25hrs, measured at room temperature after placing for 4 hrs. 2. Raise temperature to $65\pm2°$ C 90-100%RH in 2.5hrs, an keep 3 hours, cool down to 25°C in 2.5hrs. 3. Raise temperature to $65\pm2°$ C 90-100%RH in 2.5hrs, an keep 3 hours, cool down to 25°C in 2.5hrs, cool down to 25°C in 2.5hrs, keep at 25°C for 2 hrs then keep at -10°C for 3 hrs 4. Keep at 25°C 80-100%RH for 15min and vibrate at th frequency of 10 to 55 Hz to 10 Hz, measure at room temperature after placing for 1~2 hrs.		
Thermal shock		Preconditioning: Run through IR reflow for 2 times.( IPC/JEDE0 J-STD-020DClassification Reflow Profiles Condition for 1 cycle Step1: -40±2°C 30±5min Step2: 25±2°C ≤0.5min Step3: 125±2°C 30±5min Number of cycles: 500 Measured at room temperature after placing for 24±2 hrs		
Vibration		Oscillation Frequency: 10~2K~10Hz for 20 minutes Equipment: Vibration checker Total Amplitude:1.52mm±10% Testing Time: 12 hours(20 minutes, 12 cycles each of 3 orientations).		

Item	Performance	Test Condition			
Bending	Appearance: No damage. Impedance: within±15% of initial value	Shall be mounted on a FR4 substrate of the following dimensions: >=0805 inch(2012mm):40x100x1.2mm <0805 inch(2012mm):40x100x0.8mm  Bending depth: >=0805 inch(2012mm):1.2mm <0805 inch(2012mm):0.8mm duration of 10 sec.			
Shock	Inductance: within±10% of initial value Q: Shall not exceed the specification value. RDC: within ±15% of initial value and shall not exceed the specification value	Type Peak Normal Wave value duration (D) Wave form (Vi)ft/sec			
	CACCO THE SPECIMENTAL VALUE	SMD         50         11         Half-sine         11.3			
		Lead         50         11         Half-sine         11.3			
Solder ability	More than 95% of the terminal electrode should be covered with solder.	Preheat: 150°C,60sec.。 Solder: Sn96.5% Ag3% Cu0.5% Temperature: 245±5°C。 Flux for lead free: Rosin. 9.5%。 Dip time: 4±1sec。 Depth: completely cover the termination			
Resistance to Soldering Heat		Depth: completely cover the termination  Temperature(°C) Time(s) Temperature ramp/immersion and emersion rate heat cycles (solder temp) 10 ±1 25mm/s ±6 mm/s 1			
Terminal Strength	Appearance: No damage. Impedance: within±15% of initial value Inductance: within±10% of initial value Q: Shall not exceed the specification value. RDC: within ±15% of initial value and shall not exceed the specification value e	Preconditioning: Run through IR reflow for 2 times. (IPC/JEDEC J-STD-020DClassification Reflow Profiles With the component mounted on a PCB with the device to be tested, apply a force(>0805:1kg , <=0805:0.5kg)to the side of a device being tested. This force shall be applied for 60 +1 seconds. Also the force shall be applied gradually as not to apply a shock to the component being tested.			

Note: When there are questions concerning measurement result: measurement shall be made after 48 ± 2 hours of recovery under the standard condition.

## 7. Soldering and Mounting

#### 7-1. Soldering

Mildly activated rosin fluxes are preferred. TAI-TECH terminations are suitable for all wave and re-flow soldering systems. If hand soldering cannot be avoided, the preferred technique is the utilization of hot air soldering tools.


#### 7-1.1 Solder re-flow:

Recommended temperature profiles for re-flow soldering in Figure 1.

#### 7-1.2 Soldering Iron(Figure 2):


Products attachment with a soldering iron is discouraged due to the inherent process control limitations. In the event that a soldering iron must be employed the following precautions are recommended.

- Preheat circuit and products to 150°C Never contact the ceramic with the iron tip Use a 20 watt soldering iron with tip diameter of 1.0mm
- · 355°C tip temperature (max) 
  1.0mm tip diameter (max) 
  Limit soldering time to 4~5 sec.



Reflow times: 3 times max.


Fig.1



Iron Soldering times: 1 times max.

Fig.2


#### 7-2. Recommended PC Board Pattern



L(mm)	G(mm)	H(mm)
2.9	0.8	2.4


## 8. Packaging Information


#### 8-1. Reel Dimension



Туре	A(mm)	B(mm)	C(mm)	D(mm)
7"x8mm	8.4±1.0	50 min.	13±0.8	178±2

#### 8-2. Tape Dimension / 8mm






#### 8-3. Packaging Quantity

Chip size	252012
Chip / Reel	2000

#### 8-4. Tearing Off Force



The force for tearing off cover tape is 15 to 80 grams in the arrow direction under the following conditions.

Room Temp.	Room Humidity	Room atm	Tearing Speed
(℃)	(%)	(hPa)	mm/min
5~35	45~85	860~1060	300

## **Application Notice**

- · Storage Conditions(component level)
- To maintain the solderability of terminal electrodes:
- 1. TAI-TECH products meet IPC/JEDEC J-STD-020D standard-MSL, level 1.
- 3. Recommended products should be used within 12 months form the time of delivery.
- 4. The packaging material should be kept where no chlorine or sulfur exists in the air.
- · Transportation
  - 1. Products should be handled with care to avoid damage or contamination from perspiration and skin oils.
  - 2. The use of tweezers or vacuum pick up is strongly recommended for individual components.
  - 3. Bulk handling should ensure that abrasion and mechanical shock are minimized.

# **9.Typical Performance Curves**

